

### Overview

#### HPE SimpliVity 380

HPE SimpliVity 380, based on the HPE ProLiant DL380 Gen10 and Gen10 Plus Servers, is a compact, scalable, 2U rack-mounted building block that delivers integrated server, storage, and storage networking services. Adaptable for diverse virtualized workloads, the secure 2U HPE SimpliVity 380 Gen10 and Gen10 Plus delivers world-class performance with the right balance of expandability and scalability. It also provides a complete set of advanced functionalities that enable dramatic improvements to the efficiency, management, protection, and performance at a fraction of the cost and complexity of today's traditional infrastructure stack.



**HPE SimpliVity 380 Gen10/Gen10 Plus**

#### What's New

HPE SimpliVity is now supported with HPE GreenLake Private Cloud Business Edition.

- Customers can leverage features for HPE SimpliVity environment such as viewing federated clusters, and VM provisioning operations
- Additional services on the HPE GreenLake platform such HPE GreenLake for Backup and Recovery Service and be leveraged to backup to cloud\*
- Customer can also manage public cloud infrastructure and leverage other additional capabilities which will be offered on the platform in the future.

The core feature set includes:

- Global dash boarding (VM and Clusters information, capacity details/trends, performance details/trends, alerts, protection levels)
- Simple VM provisioning wizard for both on-prem and public cloud instances including VM power cycle and on-prem VM migration operations

Prerequisites:

- A deployed and running HPE SimpliVity environment
- HPE SimpliVity software: HPE SimpliVity 4.1.3 or higher (for tested functionality).
- VMware Supported Versions - vCenter Server: 6.7, 7.0 [U3 -U1]
- Current HPE SimpliVity customers with OmniStack LTU licenses with active contracts are entitled to use HPE GreenLake for Private Cloud Business Edition.

#### Notes:

- [Provided there is HPE GreenLake for Backup and Recovery service QuickSpecs - https://www.hpe.com/psnow/doc/a50004269enw?section=Document%20Types&r=none](https://www.hpe.com/psnow/doc/a50004269enw?section=Document%20Types&r=none)

## Overview

- [HPE GreenLake for Private Cloud Business edition QuickSpecs](https://psnow.ext.hpe.com/doc/a50004281enw)  
<https://psnow.ext.hpe.com/doc/a50004281enw>

- HPE SimpliVity now supports the DL380 Gen10 Plus server powered by the 3<sup>rd</sup> Generation Intel® Xeon® Scalable Ice Lake Processors
- Higher CPU Core Count, Memory and Network Adapter bandwidth with HPE SimpliVity 380 Gen10 Plus
- Support for HPE 3.84TB SATA SSD drives on HPE SimpliVity 380 Gen10 Plus
- Support for Broadcom MR216i-p on SimpliVity 380 Gen10 Plus
- Support for NS204i-p boot drive controllers on both HPE SimpliVity 380 Gen10 and Gen10 Plus nodes
- NVIDIA A30, A16, A2 and T4 for next generation, intelligent workloads on SimpliVity 380 Gen10 Plus
- HPE SimpliVity now supports Single Disk and Dual Disk resiliency options at the time of Deployment with additional SSD configurations for HPE SimpliVity 380 G and HPE SimpliVity 380 Gen10 Plus.

**Notes:** For VMware and HW compatibility and software details, please visit:

<https://www.hpe.com/info/simplivity-interop-doc> , [HPE Support Center portal](#) and [SimpliVity Drivers and Software](#)

### Scalable and Configurable

- Expandable in 1 node increments up to 96 total nodes
- Processor - Choice of Intel® Xeon® Scalable Processors
- Memory - 128GB to 8192GB (Per node depending on the platform and configuration)
- Network – 100Gb, 10/25Gb, 1Gb (depending on the platform and configuration)
- Power – Redundant
- Virtualization Software and Licensing
- All in a compact 2U form factor

**Notes:**

- It is strongly recommended that an HPE SimpliVity 380 cluster have a minimum of two nodes to realize the full benefits of the high availability hyperconverged solution.
- A single cluster supports up to 16 nodes. A single federation supports up to 96 nodes. See product documentation for details.

### Software Features

- SimpliVity now supports HPE GreenLake for Private Cloud Business Edition Cloud Console—offered on the HPE GreenLake edge-to-cloud platform (SW 4.1.3+ is required).
- VMware vSphere
- HPE SimpliVity management plugin for VMware vCenter
- HPE Backup Archive to HPE Cloud Bank
- HPE StoreOnce Integration with Data Immutability
- Optional Data Encryption support
- Optional RapidDR support- HPE SimpliVity RapidDR is targeted to address SMB and Edge IT generalist persona DR orchestration needs with stringent SLAs around Recovery Point Objectives (RPOs) and Recovery Time Objectives (RTOs)

**Notes:**

- For RapidDR information, please see the [HPE SimpliVity RapidDR Data Sheet and QuickSpecs](#)
  - o QuickSpecs: <https://h20195.www2.hpe.com/v2/getdocument.aspx?docname=a00018755enw>
- HPE SimpliVity 380 supports VMware vSphere & vCenter 7.0
- For VMware and HW compatibility, please see the [HPE SimpliVity OmniStack Interoperability Guide](#)  
<https://www.hpe.com/info/simplivity-interop-doc> or [HPE Support Center portal](#)



---

## Overview

### VMware Software

- A valid VMware vSphere license is required for each host (16-core minimum license per-host needed).
- License types offered by VMware,
  - vSphere Foundation
  - vSphere Standard
  - vSphere Essentials Plus Kit

VMware licenses may be available through other sales channels such as distributors.

---

### Hardware Availability Features

- Cluster expansion without downtime
  - Choice of Single Disk resiliency or Dual Disk resiliency on HPE SimpliVity 380 G/Gen10 Plus nodes
  - Hot-pluggable SSD
  - Redundant power supplies
  - Integrated storage controller with battery-backed cache
  - HPE ProLiant Integrated Lights-Out Advanced (iLO) 5 Remote Management
- 

### Services

- HPE Services full suite of support offerings (Tech Care, Tech Care and Complete Care).
- Remote support technology to provide 24x7 secure remote support

**Notes:** For the best support experience, [HPE Services Installation Services](#) and [24x7x365 support](#) recommended.

---



## Standard Features

### Features

HPE SimpliVity 380 Gen10 Plus (Networking Choice (NC) Model)	
<b>Node Size</b>	2U
<b>Processors</b>	2x 3 <sup>rd</sup> Generation Intel® Xeon® Scalable Ice Lake Processors 8 to 40 cores selectable, 1 or 2CPU options
<b>Memory</b>	128GB to 4096GB per socket selectable
<b>Boot Controller</b>	Choice of Smart Array MR216i-p, E208i-p or NS204i-p boot controllers
<b>Boot Disks</b>	480 GB SSD Boot disks (Not required with NS204i-p)
<b>Storage</b>	<p>All Flash Storage Options (RI)</p> <p>Capacity Options:</p> <ul style="list-style-type: none"> <li>6 x 1.92TB SSD – 7.5TB (usable)</li> <li>8 x 1.92TB SSD – 10TB (usable)</li> <li>9x 1.92TB SSD – 10TB (usable)</li> <li>12 x 1.92TB SSD – 15TB (usable)</li> <li>6 x 3.84TB SSD – 15TB (usable)</li> <li>8 x 3.84TB SSD – 21TB (usable)</li> <li>9x 3.84TB SSD – 21TB (usable)</li> <li>12 x 3.84TB SSD – 32TB (usable)</li> </ul> <p><b>Notes:</b></p> <ul style="list-style-type: none"> <li>Single Disk resiliency is supported on x6, x8 and x12 options</li> <li>Dual Disk resiliency is supported on x6, x9 and x12 options</li> <li>Some Configurations may require exception approval</li> </ul>
<b>Power Supplies</b>	<p>HPE 800W Flex Slot Titanium Hot Plug Low Halogen Power Supply Kit</p> <p>HPE 800W Flex Slot -48VDC Hot Plug Low Halogen Power Supply Kit</p> <p>HPE 800W Flex Slot Universal Hot Plug Low Halogen Power Supply Kit</p> <p>HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit</p> <p>HPE 1000W Flex Slot Titanium Hot Plug Power Supply Kit</p> <p>HPE 1600W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit</p> <p>HPE 1600W Flex Slot -48VDC Hot Plug Power Supply Kit</p> <p>HPE 1600W -48VDC Power Cable Lug Kit</p> <p>HPE 1800W-2200W Flex Slot Titanium Hot Plug Low Halogen Power Supply Kit</p>
<b>Hardware Warranty</b>	Server Warranty includes 3-Year Parts, 3-Year Labor, 3-Year Onsite support with next business day response
<b>Hardware Support</b>	3-year HPE SimpliVity 380 Gen10 Plus solution support (required)

#### Notes:

- Warranty for SSDs is subject to maximum usage limitations. Maximum usage limit is the maximum amount of data that can be written to the drive. Drives that have reached this limit will not be eligible for replacement.
- Two power supplies per node are required for redundancy. 800W power supplies are only supported with specific configurations.



## Standard Features

HPE SimpliVity 380 Gen10	
<b>Node Size</b>	2U
<b>Processors</b>	2x Intel® Xeon® Scalable Processors 8 to 28 cores selectable, 1 or 2CPU options
<b>Memory</b>	144GB to 3072GB per node selectable
<b>Storage</b>	Two All Flash Storage Options (4000/6000 Series) and Five Capacity Points: Extra Small - 5 x 960GB SSD Kit Small - 5 x 1.92TB SSD Kit Medium - 9x 1.92TB SSD Kit Large - 12 x 1.92TB SSD Kit Extra Large – 12 x 3.84TB SSD Kit (4000 Series only)
<b>Network Ports</b>	Ethernet 1Gb LOM embedded, 10Gb FLOM
<b>Power Supplies</b>	HPE 800W FS Plat Hot Plug Power Supply Kit HPE 800W FS -48VDC Hot Plug Power Supply Kit HPE 800W FS Titanium Hot Plug Power Supply Kit HPE 800W FS Universal Hot Plug Power Supply Kit HPE 1600W FS Platinum Hot Plug LH Power Supply Kit HPE 1800W-2200W Flex Slot Titanium Hot Plug Low Halogen Power Supply Kit
<b>Hardware Warranty</b>	Server Warranty includes 3-Year Parts, 3-Year Labor, 3-Year Onsite support with next business day response
<b>Hardware Support</b>	3-year HPE SimpliVity 380 Gen10 solution support (required)

### Notes:

- Warranty for SSDs is subject to maximum usage limitations. Maximum usage limit is the maximum amount of data that can be written to the drive. Drives that have reached this limit will not be eligible for replacement.
- Two power supplies per node are required for redundancy. 800W power supplies are only supported with specific configurations.



## Standard Features

HPE SimpliVity 380 Gen10 G (Networking Choice (NC) Models)	
<b>Node Size</b>	2U
<b>Processors</b>	2x Intel® Xeon® Scalable Processors 8 to 28 cores selectable, 1 or 2CPU options
<b>Memory</b>	128GB to 3072GB per node selectable
<b>Boot Controller</b>	Choice of Smart Array E208i-p or NS204i-p boot controllers
<b>Boot Disks</b>	Choice of 300 GB HDD or 480 GB SSD Boot disks
<b>Storage</b>	<p>Two All Flash Storage Options (RI/MU) Capacity Options:</p> <ul style="list-style-type: none"> <li>6 x 1.92TB SSD Kit – 7.5TB (usable)</li> <li>8 x 1.92TB SSD Kit – 10TB (usable)</li> <li>9x 1.92TB SSD Kit – 10TB (usable)</li> <li>12 x 1.92TB SSD Kit- 15TB (usable)</li> <li>16 x 1.92TB SSD Kit- 20TB (usable)</li> <li>18 x 1.92TB SSD Kit- 20TB (usable)</li> <li>24 x 1.92TB SSD Kit- 32TB (usable)</li> </ul> <p><b>Notes:</b></p> <ul style="list-style-type: none"> <li>– Single Disk resiliency is supported on x6, x8, x12, x16 and x24 options</li> <li>– Dual Disk resiliency is supported on x6, x9, x12, x18 and x24 options</li> <li>– Mixed Use (MU) options are NOT supported on x9, x18 or x24 options</li> </ul>
<b>Network Ports</b>	<p>10Gb FLOM</p> <p><b>Notes:</b> Networking Choice (NC) models do not include an embedded NIC, additional options available via stand-up card NIC adapters to better suit customer needs</p>
<b>Power Supplies</b>	<p>HPE 800W FS Plat Hot Plug Power Supply Kit HPE 800W FS -48VDC Hot Plug Power Supply Kit HPE 800W FS Titanium Hot Plug Power Supply Kit HPE 800W FS Universal Hot Plug Power Supply Kit HPE 1600W FS Platinum Hot Plug LH Power Supply Kit HPE 1800W-2200W Flex Slot Titanium Hot Plug Low Halogen Power Supply Kit</p>
<b>Hardware Warranty</b>	Server Warranty includes 3-Year Parts, 3-Year Labor, 3-Year Onsite support with next business day response
<b>Hardware Support</b>	3-year HPE SimpliVity 380 Gen10 solution support (required)

### Notes:

- Warranty for SSDs is subject to maximum usage limitations. Maximum usage limit is the maximum amount of data that can be written to the drive. Drives that have reached this limit will not be eligible for replacement.
- Two power supplies per node are required for redundancy. 800W power supplies are only supported with specific configurations.
- Network Choice (NC) models do not include an Ethernet 1Gb LOM embedded NIC. A pre-selected FlexibleLOM is included in the configuration with additional options available via stand-up card NIC adapters.



## Standard Features

HPE SimpliVity 380 Gen10 G	
<b>Node Size</b>	2U
<b>Processors</b>	2x Intel® Xeon® Scalable Processors 8 to 28 cores selectable, 1 or 2CPU options
<b>Memory</b>	128GB to 3072GB per node selectable
<b>Boot Controller</b>	Choice of Smart Array E208i-p or NS204i-p boot controllers
<b>Boot Disks</b>	Choice of 300 GB HDD or 480 GB SSD Boot disks
<b>Storage</b>	<p>Two All Flash Storage Options (RI/MU)</p> <p>Capacity Options:</p> <ul style="list-style-type: none"> <li>6 x 1.92TB SSD Kit – 7.5TB (usable)</li> <li>8 x 1.92TB SSD Kit – 10TB (usable)</li> <li>9x 1.92TB SSD Kit – 10TB (usable)</li> <li>12 x 1.92TB SSD Kit- 15TB (usable)</li> <li>16 x 1.92TB SSD Kit- 20TB (usable)</li> <li>18 x 1.92TB SSD Kit- 20TB (usable)</li> <li>24 x 1.92TB SSD Kit- 32TB (usable)</li> </ul> <p><b>Notes:</b></p> <ul style="list-style-type: none"> <li>– Single Disk resiliency is supported on x6, x8, x12, x16 and x24 options</li> <li>– Dual Disk resiliency is supported on x6, x9, x12, x18 and x24 options</li> <li>– Mixed Use (MU) options are NOT supported on x9, x18 or x24 options</li> </ul>
<b>Network Ports</b>	Ethernet 1Gb LOM embedded, 10Gb FLOM
<b>Power Supplies</b>	<p>HPE 800W FS Plat Hot Plug Power Supply Kit</p> <p>HPE 800W FS -48VDC Hot Plug Power Supply Kit</p> <p>HPE 800W FS Titanium Hot Plug Power Supply Kit</p> <p>HPE 800W FS Universal Hot Plug Power Supply Kit</p> <p>HPE 1600W FS Platinum Hot Plug LH Power Supply Kit</p> <p>HPE 1800W-2200W Flex Slot Titanium Hot Plug Low Halogen Power Supply Kit</p>
<b>Hardware Warranty</b>	Server Warranty includes 3-Year Parts, 3-Year Labor, 3-Year Onsite support with next business day response
<b>Hardware Support</b>	3-year HPE SimpliVity 380 Gen10 solution support (required)

### Notes:

- Warranty for SSDs is subject to maximum usage limitations. Maximum usage limit is the maximum amount of data that can be written to the drive. Drives that have reached this limit will not be eligible for replacement.
- Two power supplies per node are required for redundancy. 800W power supplies are only supported with specific configurations.



## Standard Features

HPE SimpliVity 380 Gen10 H (Networking Choice (NC) Models)	
<b>Node Size</b>	2U SFF
<b>Processors</b>	2x Intel® Xeon® Scalable Processors 8 to 28 cores selectable, 1 or 2CPU options
<b>Memory</b>	192GB to 3072GB per node selectable
<b>Storage</b>	SFF General Purpose Virtualization: 4x 1.92TB, 20 x 1.2TB HDD- 20TB (usable)
<b>Network Ports</b>	10Gb FLOM <b>Notes:</b> Networking Choice (NC) models do not include an embedded NIC, additional options available via stand-up card NIC adapters to better suit customer needs
<b>Power Supplies</b>	HPE 800W FS Plat Hot Plug Power Supply Kit HPE 800W FS -48VDC Hot Plug Power Supply Kit HPE 800W FS Titanium Hot Plug Power Supply Kit HPE 800W FS Universal Hot Plug Power Supply Kit HPE 1600W FS Platinum Hot Plug LH Power Supply Kit HPE 1800W-2200W Flex Slot Titanium Hot Plug Low Halogen Power Supply Kit
<b>Hardware Warranty</b>	Server Warranty includes 3-Year Parts, 3-Year Labor, 3-Year Onsite support with next business day response
<b>Hardware Support</b>	3-year HPE SimpliVity 380 Gen10 solution support (required)

### Notes:

- Warranty for SSDs is subject to maximum usage limitations. Maximum usage limit is the maximum amount of data that can be written to the drive. Drives that have reached this limit will not be eligible for replacement.
- Two power supplies per node are required for redundancy. 800W power supplies are only supported with specific configurations.
- Network Choice (NC) models do not include an Ethernet 1Gb LOM embedded NIC. A pre-selected FlexibleLOM is included in the configuration with additional options available via stand-up card NIC adapters.

HPE SimpliVity 380 Gen10 H	
<b>Node Size</b>	2U SFF
<b>Processors</b>	2x Intel® Xeon® Scalable Processors 8 to 28 cores selectable, 1 or 2CPU options
<b>Memory</b>	192GB to 3072GB per node selectable
<b>Storage</b>	SFF General Purpose Virtualization: 4x 1.92TB, 20 x 1.2TB HDD- 20TB (usable)
<b>Network Ports</b>	Ethernet 1Gb LOM embedded, 10Gb FLOM
<b>Power Supplies</b>	HPE 800W FS Plat Hot Plug Power Supply Kit HPE 800W FS -48VDC Hot Plug Power Supply Kit HPE 800W FS Titanium Hot Plug Power Supply Kit HPE 800W FS Universal Hot Plug Power Supply Kit HPE 1600W FS Platinum Hot Plug LH Power Supply Kit HPE 1800W-2200W Flex Slot Titanium Hot Plug Low Halogen Power Supply Kit
<b>Hardware Warranty</b>	Server Warranty includes 3-Year Parts, 3-Year Labor, 3-Year Onsite support with next business day response
<b>Hardware Support</b>	3-year HPE SimpliVity 380 Gen10 solution support (required)

### Notes:

- Warranty for SSDs is subject to maximum usage limitations. Maximum usage limit is the maximum amount of data that can be written to the drive. Drives that have reached this limit will not be eligible for replacement.
- Two power supplies per node are required for redundancy. 800W power supplies are only supported with specific configurations.





---

## Standard Features

### Benefits

#### **HPE InfoSight for HPE SimpliVity enables predictive data analytics**

For HPE SimpliVity nodes HPE InfoSight is free with no license requirements and provides system details at the federation, cluster, and host level for historic capacity utilization, trends, resource consumption and prediction. Alleviates support issues and reduces operational expenses with automated wellness alerts and case creation. Provides a unified view of HPE SimpliVity assets such as Datastore, VM, Backups, Capacity, and IOPS. It now supports HPE InfoSight for Server Integration for HPE SimpliVity combining the machine learning and predictive analytics of HPE InfoSight with the health and performance monitoring of Active Health System (AHS) and HPE iLO to optimize performance, predict, and prevent problems. This provides automatic collection and analysis of the sensor and telemetry data (for heat fans, DIMMS as examples) from AHS to derive insights from the behaviors of the install base to provide recommendations to resolve problems and improve performance.

#### **Fully integrated system**

Combines x86 resources, storage, and storage networking in a single hyperconverged system. Simplifies management and delivers great cost efficiency and agility with increased visibility and control.

#### **Peak and predictable performance**

The all-flash solution provides predictable and linear performance at near-wire speeds with reduced latency. Inline deduplication, compression, and optimization helps minimize I/O and network traffic, improving performance while delivering great storage and bandwidth efficiency.

#### **Scale in and scale out**

Easily expand or shrink configurations as your needs change. Each node supports a large number of fully protected virtual machines (VMs), with the networked collection of nodes at both local and remote sites managed as a single entity.

#### **VM centricity and mobility**

Enables all actions, policies, and management at the VM level. Global unified management and integration with established administrative systems streamline operations and improve IT agility.

#### **Dramatic TCO reduction**

Drastically reduce the need to purchase multiple discrete components, optimize storage capacity with guaranteed 10:1 data efficiency, and prevent over-provisioning for performance and capacity with on-demand expansion.

#### **Cloud storage**

HPE SimpliVity with Backup Archive to Cloud Bank feature enables cloud storage via the regular Catalyst store to CloudBank store for long-term retention

#### **Secondary, centralized backup**

HPE SimpliVity with HPE StoreOnce protects data center and distributed edge sites by easily and efficiently replicating applications and data directly to a centralized HPE StoreOnce appliance for compliance and long-term retention requirements. HPE StoreOnce also provides Data Immutability for better protection against ransomware attacks.

---



---

## Standard Features

### Software Overview

#### Pre-integrated software

- HPE SimpliVity Startup Wizard

#### Virtualization Platform Software and Licenses

- HPE SimpliVity 380 Gen10 and Gen10 Plus support VMware vSphere ESXi.
- VMware vSphere installation is performed by HPE when ordering HPE SimpliVity 380 nodes
- Valid licenses for the following VMware software components are required when ordering HPE SimpliVity 380 nodes
  - VMware vSphere license(s) depending on core count. (16-core minimum license per-host)
  - VMware vCenter license

#### Notes:

- HPE SimpliVity 380 supports VMware vSphere & vCenter 7.0
- For VMware and HW compatibility, please visit [HPE Support Center portal](https://www.hpe.com/info/simplivity-interop-doc) or <https://www.hpe.com/info/simplivity-interop-doc>

#### Management

- HPE InfoSight
  - VMware vCenter
  - HPE SimpliVity management plugin for VMware vCenter
- 



---

## Service and Support

### HPE Services

No matter where you are in your digital transformation journey, you can count on HPE Services to deliver the expertise you need when, where and how you need it. From planning to deployment, ongoing operations and beyond, our experts can help you realize your digital ambitions.

<https://www.hpe.com/services>

---

### Consulting Services

No matter where you are in your journey to hybrid cloud, experts can help you map out your next steps. From determining what workloads should live where, to handling governance and compliance, to managing costs, our experts can help you optimize your operations.

<https://www.hpe.com/services/consulting>

---

### HPE Managed Services

HPE runs your IT operations, providing services that monitor, operate, and optimize your infrastructure and applications, delivered consistently and globally to give you unified control and let you focus on innovation.

[HPE Managed Services | HPE](#)

---

### Operational services

Optimize your entire IT environment and drive innovation. Manage day-to-day IT operational tasks while freeing up valuable time and resources. Meet service-level targets and business objectives with features designed to drive better business outcomes.

<https://www.hpe.com/services/operational>

---

### HPE Complete Care Service

HPE Complete Care Service is a modular, edge-to-cloud IT environment service designed to help optimize your entire IT environment and achieve agreed upon IT outcomes and business goals through a personalized experience. All delivered by an assigned team of HPE Services experts. HPE Complete Care Service provides:

- A complete coverage approach -- edge to cloud
- An assigned HPE team
- Modular and fully personalized engagement
- Enhanced Incident Management experience with priority access
- Digitally enabled and AI driven customer experience

<https://www.hpe.com/services/complecare>

---

### HPE Tech Care Service

HPE Tech Care Service is the operational support service experience for HPE products. The service goes beyond traditional support by providing access to product specific experts, an AI driven digital experience, and general technical guidance to not only reduce risk but constantly search for ways to do things better. HPE Tech Care Service delivers a customer-centric, AI driven, and digitally enabled customer experience to move your business forward. HPE Tech Care Service is available in three response levels. Basic, which provides 9x5 business hour availability and a 2-hour response time. Essential which provides a 15-minute response time 24x7 for most enterprise level customers, and Critical which includes a 6-hour repair commitment where available and outage management response for severity 1 incidents.

<https://www.hpe.com/services/techcare>

---



## Service and Support

### HPE Lifecycle Services

HPE Lifecycle Services provide a variety of options to help maintain your HPE systems and solutions at all stages of the product lifecycle. A few popular examples include:

- Lifecycle Install and Startup Services: Various levels for physical installation and power on, remote access setup, installation and startup, and enhanced installation services with the operating system.
- HPE Firmware Update Analysis Service: Recommendations for firmware revision levels for selected HPE products, taking into account the relevant revision dependencies within your IT environment.
- HPE Firmware Update Implementation Service: Implementation of firmware updates for selected HPE server, storage, and solution products, taking into account the relevant revision dependencies within your IT environment.
- Implementation assistance services: Highly trained technical service specialists to assist you with a variety of activities, ranging from design, implementation, and platform deployment to consolidation, migration, project management, and onsite technical forums.
- HPE Service Credits: Access to prepaid services for flexibility to choose from a variety of specialized service activities, including assessments, performance maintenance reviews, firmware management, professional services, and operational best practices.

**Notes:** To review the list of Lifecycle Services available for your product go to:

<https://www.hpe.com/services/lifecycle>

For a list of the most frequently purchased services using service credits, see the [HPE Service Credits Menu](#)

---

### Other Related Services from HPE Services:

#### HPE Education Services

Training and certification designed for IT and business professionals across all industries. Broad catalogue of course offerings to expand skills and proficiencies in topics ranging from cloud and cybersecurity to AI and DevOps. Create learning paths to expand proficiency in a specific subject. Schedule training in a way that works best for your business with flexible continuous learning options.

<https://www.hpe.com/services/training>

#### Defective Media Retention

An option available with HPE Complete Care Service and HPE Tech Care Service and applies only to Disk or eligible SSD/Flash Drives replaced by HPE due to malfunction.

Consult your HPE Sales Representative or Authorized Channel Partner of choice for any additional questions and services options.

#### Parts and Materials

HPE will provide HPE-supported replacement parts and materials necessary to maintain the covered hardware product in operating condition, including parts and materials for available and recommended engineering improvements.

Parts and components that have reached their maximum supported lifetime and/or the maximum usage limitations as set forth in the manufacturer's operating manual, product quick-specs, or the technical product data sheet will not be provided, repaired, or replaced as part of these services.

#### How to Purchase Services

Services are sold by Hewlett Packard Enterprise and Hewlett Packard Enterprise Authorized Service Partners:

- Services for customers purchasing from HPE or an enterprise reseller are quoted using HPE order configuration tools.
- Customers purchasing from a commercial reseller can find services at <https://ssc.hpe.com/portal/site/ssc/>



---

## Service and Support

### AI Powered and Digitally Enabled Support Experience

Achieve faster time to resolution with access to product-specific resources and expertise through a digital and data driven customer experience

Sign into the HPE Support Center experience, featuring streamlined self-serve case creation and management capabilities with inline knowledge recommendations. You will also find personalized task alerts and powerful troubleshooting support through an intelligent virtual agent with seamless transition when needed to a live support agent.

<https://support.hpe.com/hpesc/public/home/signin>

---

### Consume IT On Your Terms

**HPE GreenLake** edge-to-cloud platform brings the cloud experience directly to your apps and data wherever they are—the edge, colocations, or your data center. It delivers cloud services for on-premises IT infrastructure specifically tailored to your most demanding workloads. With a pay-per-use, scalable, point-and-click self-service experience that is managed for you, HPE GreenLake edge-to-cloud platform accelerates digital transformation in a distributed, edge-to-cloud world.

- Get faster time to market
- Save on TCO, align costs to business
- Scale quickly, meet unpredictable demand
- Simplify IT operations across your data centers and clouds

To learn more about HPE Services, please contact your Hewlett Packard Enterprise sales representative or Hewlett Packard Enterprise Authorized Channel Partner. Contact information for a representative in your area can be found at "Contact HPE"

<https://www.hpe.com/us/en/contact-hpe.html>

For more information

<http://www.hpe.com/services>

---



## Configuration Information

### Step 1: Begin with the base node

#### Base Node

##### Action:

- Select the base node
- Select the base node VMware tracking SKU added automatically
- User selection required for Single Disk Resiliency or Dual Disk Resiliency

Remarks	Description	SKU
	HPE SimpliVity 380 Gen10 Plus Configure-to-order Node	S1J98A
	HPE SimpliVity 380 Gen10 Plus Configure-to-order Solution Tracking	S2A12A

### Step 2: Select the hardware options to add to the base node

#### Processors

##### 3rd Generation Intel® Xeon® Scalable Processors

##### Action:

- Select CPUs for the node

Remarks	Description	SKU
32C 2.2GHz 205W	Intel Xeon-Platinum 8352Y 2.2GHz 32-core 205W Processor for HPE	P36929-B21
32C 2.6GHz 250W	Intel Xeon-Platinum 8358 2.6GHz 32-core 250W Processor for HPE	P36938-B21
36C 2.4GHz 250W	Intel Xeon-Platinum 8360Y 2.4GHz 36-core 250W Processor for HPE	P36939-B21
38C 2.4GHz 270W	Intel Xeon-Platinum 8368 2.4GHz 38-core 270W Processor for HPE	P36940-B21
40C 2.3GHz 270W	Intel Xeon-Platinum 8380 2.3GHz 40-core 270W Processor for HPE	P36941-B21
32C 2.8GHz 265W	Intel Xeon-Platinum 8362 2.8GHz 32-core 265W Processor for HPE	P45418-B21
36C 2.1GHz 195W	Intel Xeon-Platinum 8352V 2.1GHz 36-core 195W Processor for HPE	P37599-B21
32C 2.3GHz 185W	Intel Xeon-Platinum 8352M 2.3GHz 32-core 185W Processor for HPE	P45414-B21
32C 2.6GHz 240W	Intel Xeon-Platinum 8358P 2.6GHz 32-core 240W Processor for HPE	P37598-B21
18C 3.0GHz 205W	Intel Xeon-Gold 6354 3.0GHz 18-core 205W Processor for HPE	P36935-B21
28C 2.6GHz 235W	Intel Xeon-Gold 6348 2.6GHz 28-core 235W Processor for HPE	P36937-B21
16C 3.1GHz 205W	Intel Xeon-Gold 6346 3.1GHz 16-core 205W Processor for HPE	P36934-B21
32C 2.0GHz 205W	Intel Xeon-Gold 6338 2.0GHz 32-core 205W Processor for HPE	P36928-B21
28C 2.0GHz 205W	Intel Xeon-Gold 6330 2.0GHz 28-core 205W Processor for HPE	P36927-B21
16C 2.9GHz 185W	Intel Xeon-Gold 6326 2.9GHz 16-core 185W Processor for HPE	P36932-B21
24C 2.8GHz 230W	Intel Xeon-Gold 6342 2.8GHz 24-core 230W Processor for HPE	P36936-B21
24C 2.4GHz 185W	Intel Xeon-Gold 6336Y 2.4GHz 24-core 185W Processor for HPE	P36926-B21
Remarks	Description	SKU
8C 3.6GHz 165W	Intel Xeon-Gold 6334 3.6GHz 8-core 165W Processor for HPE	P36933-B21
26C 2.2GHz 185W	Intel Xeon-Gold 5320 2.2GHz 26-core 185W Processor for HPE	P36925-B21
24C 2.1GHz 165W	Intel Xeon-Gold 5318Y 2.1GHz 24-core 165W Processor for HPE	P36924-B21
12C 3.0GHz 150W	Intel Xeon-Gold 5317 3.0GHz 12-core 150W Processor for HPE	P36931-B21
8C 3.2GHz 140W	Intel Xeon-Gold 5315Y 3.2GHz 8-core 140W Processor for HPE	P36930-B21
20C 2.3GHz 150W	Intel Xeon-Silver 4316 2.3GHz 20-core 150W Processor for HPE	P36923-B21
16C 2.4GHz 135W	Intel Xeon-Silver 4314 2.4GHz 16-core 135W Processor for HPE	P36922-B21
12C 2.1GHz 120W	Intel Xeon-Silver 4310 2.1GHz 12-core 120W Processor for HPE	P36921-B21
8C 2.8GHz 105W	Intel Xeon-Silver 4309Y 2.8GHz 8-core 105W Processor for HPE	P36920-B21

#### Memory

##### Action:

- Select a memory capacity for the node
- The appropriate memory and quantity will be included by the configurator
- 1 Kit required per CPU



## Configuration Information

Remarks	Description	SKU
<b>Registered DIMMs (RDIMMs)</b>		
8 GB (1x8 GB)	HPE 8GB (1x8GB) Single Rank x8 DDR4-3200 CAS-22-22-22 Registered Smart Memory Kit	P07525-K21
16 GB (1x16 GB)	HPE 16GB (1x16GB) Single Rank x4 DDR4-3200 CAS-22-22-22 Registered Smart Memory Kit	P06029-K21
16 GB (1x16 GB)	HPE 16GB (1x16GB) Dual Rank x8 DDR4-3200 CAS-22-22-22 Registered Smart Memory Kit	P06031-K21
32 GB (1x32 GB)	HPE 32GB (1x32GB) Dual Rank x4 DDR4-3200 CAS-22-22-22 Registered Smart Memory Kit	P06033-K21
32 GB (1x32 GB)	HPE 32GB (1x32GB) Single Rank x4 DDR4-3200 CAS-22-22-22 Registered Smart Memory Kit	P40007-B21
64 GB (1x64 GB)	HPE 64GB (1x64GB) Dual Rank x4 DDR4-3200 CAS-22-22-22 Registered Smart Memory Kit	P06035-K21

### Load Reduced DIMMs (LRDIMMs)

128 GB (1x128 GB)	HPE 128GB (1x128GB) Quad Rank x4 DDR4-3200 CAS-22-22-22 Load Reduced Smart Memory Kit	P06037-K21
256 GB (1x256 GB)	HPE 256GB (1x256GB) Octal Rank x4 DDR4-3200 CAS-26-22-22 Load Reduced 3DS Smart Memory Kit	P06039-K21

**Notes:** For more information go to: <http://www.hpe.com/docs/memory-population-rules>

### Boot Device/Boot RAID Controllers

Description	SKU
HPE Smart Array E208i-p SR Gen10 (8 Internal Lanes/No Cache) 12G SAS PCIe Plug-in Controller	804394-B21
Broadcom MegaRAID MR216i-p x16 Lanes without Cache NVMe/SAS 12G Controller for HPE Gen10 Plus	632241-B21
HPE NS204i-p x2 Lanes NVMe PCIe3 x8 OS Boot Device	

#### Notes:

- User must select qty1 of the same type of controller from the above options
- If selecting NS204i-p, there is no need to select boot SSDs below

### Boot SSD Drives

Description	SKU
HPE SimpliVity 480GB SATA 6G Read Intensive SFF BC Multi Vendor SSD	S1J86A
HPE SimpliVity 960GB SATA 6G Read Intensive SFF BC Multi Vendor SSD	S1J87A

#### Notes:

- User must select qty2 of the same type of HDD/SSD
- If selecting NS204i-p Controller, there is no need to select boot SSDs since NS204i-p it comes with NVMe drives

## Networking

### PCI-e NIC Adapters

#### 1 Gigabit Ethernet adapters\*

Description	SKU
Broadcom BCM5719 Ethernet 1Gb 4-port BASE-T Adapter for HPE	P51178-B21
Intel I350-T4 Ethernet 1Gb 4-port BASE-T Adapter for HPE	P21106-B21

**Notes:** \* Can be installed in PCIe x8 Slot

#### 10 Gigabit Ethernet adapters\*

Description	SKU
Broadcom BCM57416 Ethernet 10Gb 2-port BASE-T Adapter for HPE	P26253-B21
Broadcom BCM57412 Ethernet 10Gb 2-port SFP+ Adapter for HPE	P26259-B21
Marvell QL41132HLRJ Ethernet 10Gb 2-port BASE-T Adapter for HPE	P08437-B21



## Configuration Information

Marvell QL41132HLCU Ethernet 10Gb 2-port SFP+ Adapter for HPE	P21933-B21
Marvell QL41134HLCU Ethernet 10Gb 4-port SFP+ Adapter for HPE	P10094-B21

**Notes:** \* Can be installed in PCIe x8 Slot

### 10/25 Gigabit Ethernet adapters

#### Description

	SKU
Broadcom BCM57414 Ethernet 10/25Gb 2-port SFP28 Adapter for HPE	P26262-B21
Mellanox MCX512F-ACHT Ethernet 10/25Gb 2-port SFP28 Adapter for HPE	P13188-B21
Marvell QL41232HLCU Ethernet 10/25Gb 2-port SFP28 Adapter for HPE	P22702-B21

### 100 Gigabit Ethernet adapters

#### Description

	SKU
HPE Ethernet 100Gb 1-port QSFP28 PCIe3 x16 MCX515A-CCAT Adapter	P31246-B21

### OCP 3.0 NIC Adapters\*

#### Description

	SKU
Broadcom BCM5719 Ethernet 1Gb 4-port BASE-T OCP3 Adapter for HPE	P51181-B21
Broadcom BCM57416 Ethernet 10Gb 2-port BASE-T OCP3 Adapter for HPE	P10097-B21
Broadcom BCM57412 Ethernet 10Gb 2-port SFP+ OCP3 Adapter for HPE	P26256-B21
Broadcom BCM57414 Ethernet 10/25Gb 2-port SFP28 OCP3 Adapter for HPE	P10115-B21
Intel I350-T4 Ethernet 1Gb 4-port BASE-T OCP3 Adapter for HPE	P08449-B21
Marvell QL41132HQRJ Ethernet 10Gb 2-port BASE-T OCP3 Adapter for HPE	P10103-B21
Marvell QL41132HQCUC Ethernet 10Gb 2-port SFP+ OCP3 Adapter for HPE	P08452-B21
Marvell QL41232HQCUC Ethernet 10/25Gb 2-port SFP28 OCP3 Adapter for HPE	P10118-B21
Mellanox MCX562A-ACAI Ethernet 10/25Gb 2-port SFP28 OCP3 Adapter for HPE	P10112-B21

**Notes:**\* Please refer to the [HPE ProLiant DL380 Gen10 Plus Server - QuickSpecs](#).

### Fiber Channel Host Bus Adapters\*

#### Description

	SKU
HPE SN1200E 16Gb Single Port Fibre Channel Host Bus Adapter	Q0L13A
HPE SN1200E 16Gb Dual Port Fibre Channel Host Bus Adapter	Q0L14A
HPE SN1610E 32Gb 1-port Fibre Channel Host Bus Adapter	R2J62A
HPE SN1610E 32Gb 2-port Fibre Channel Host Bus Adapter	R2J63A
HPE SN1700E 64Gb 1-port Fibre Channel Host Bus Adapter	R7N77A
HPE SN1700E 64Gb 2-port Fibre Channel Host Bus Adapter	R7N78A
HPE SN1100Q 16Gb Single Port Fibre Channel Host Bus Adapter	P9D93A
HPE SN1100Q 16Gb Dual Port Fibre Channel Host Bus Adapter	P9D94A
HPE SN1610Q 32Gb 1-port Fibre Channel Host Bus Adapter	R2E08A
HPE SN1610Q 32Gb 2-port Fibre Channel Host Bus Adapter	R2E09A

**Notes:** \*

- Please refer to the [HPE ProLiant DL380 Gen10 Plus Server - QuickSpecs](#).
- All the HBA cards to be managed outside of SimpliVity manageability and orchestration.

### Graphics Accelerator Cards (GPUs)\*

#### Description

	SKU
NVIDIA T4 16GB Computational Accelerator for HPE	ROW29C
NVIDIA A2 16GB PCIe Non-CEC Accelerator for HPE	R9H23C
NVIDIA A16 64GB PCIe Non-CEC Accelerator for HPE	R8T26C
NVIDIA A30 PCIe Non-CEC Accelerator for HPE	R9S38C

**Notes:**\* Please refer to the [HPE ProLiant DL380 Gen10 Plus Server - QuickSpecs](#)





## Configuration Information

### Power Supplies

Description	SKU
HPE 800W Flex Slot Titanium Hot Plug Low Halogen Power Supply Kit	865438-B21
HPE 800W Flex Slot -48VDC Hot Plug Low Halogen Power Supply Kit	865434-B21
HPE 800W Flex Slot Universal Hot Plug Low Halogen Power Supply Kit	865428-B21
HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit	P38995-B21
HPE 1000W Flex Slot Titanium Hot Plug Power Supply Kit	P03178-B21
HPE 1600W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit	P38997-B21
HPE 1600W Flex Slot -48VDC Hot Plug Power Supply Kit	P17023-B21
HPE 1600W -48VDC Power Cable Lug Kit	P36877-B21
HPE 1800W-2200W Flex Slot Titanium Hot Plug Power Supply Kit	P44712-B21

#### Notes:

- The power supply requirements can vary based on configuration and environment 800W Power Supply is only supported with specific configurations. Please refer to HPE Power Advisor for proper power sizing.
- All configured nodes ship with a standard 6 foot IEC C-13/C-14 jumper cord (AOK02a). This jumper cord is also included with each standard AC power supply option kit. If a different power cord is required, please check the ProLiant Power Cables web page: <https://h20195.www2.hp.com/v2/getpdf.aspx/4AA6-6836ENW.pdf>

### HPE High Performance Heatsinks

Description	SKU
HPE ProLiant DL380 Gen10 Plus High Performance Heat Sink Kit	P27095-B21

**Notes:** Included in OCA by default

#### Storage

##### Action:

- Select one storage kit for the node
- Choose read intensive drive configuration
- The appropriate OmniStack software will be included by the configurator
- Only the Read Intensive SSD drives are supported

### Read Intensive

Description	SKU
HPE SimpliVity 1.92TB SATA 6G Read Intensive SFF BC Multi Vendor SSD	S1J88A
HPE SimpliVity 3.84TB SATA 6G Read Intensive SFF BC Multi Vendor SSD	S1J89A

#### 1.92TB SSD Options

- Qty 6 of S1J88A is required for HPE SimpliVity 380 Gen10 Plus 6x SSD -Usable Capacity 7.5TB
- Qty 8 of S1J88A is required for HPE SimpliVity 380 Gen10 Plus 8x SSD -Usable Capacity 10TB
- Qty 9 of S1J88A- is required for HPE SimpliVity 380 Gen10 Plus 9x SSD- Usable Capacity 10TB

Or

#### 3.84TB SSD Options

- Qty 6 of S1J89A is required for HPE SimpliVity 380 Gen10 Plus 6x SSD. Usable Capacity 15TB
- Qty 8 of S1J89A is required for HPE SimpliVity 380 Gen10 Plus 8x SSD. Usable Capacity 21TB
- Qty 9 of S1J89A- is required for HPE SimpliVity 380 Gen10 Plus 9x SSD. Usable Capacity 21TB
- Qty 12 of S1J89A- is required for HPE SimpliVity 380 Gen10 Plus 12x SSD. Usable Capacity 32TB

**Notes:** Some configurations may require exception approval



## Configuration Information

### Usable Capacity

**Notes:** Usable capacity is the capacity available after RAID and system overheads have been removed, before deduplication and compression is applied. In the case of Dual Disk Resiliency the usable capacity will be different

### Step 3: The software license that corresponds to the node configuration will be automatically added

#### HPE SimpliVity Software

**Action:** Based on the number of CPUs in the node, the appropriate software will be included by the configurator.

1.92TB SSD 1 Processor based model selection:

- Qty 1 of S1N03A is required for HPE SimpliVity 380 Gen10 Plus 6x SSD
- Qty 1 of S1N04A is required for HPE SimpliVity 380 Gen10 Plus 8x SSD
- Qty 1 of S1N05A- is required for HPE SimpliVity 380 Gen10 Plus 9x SSD

1.92TB SSD 2 Processor based model selection:

- Qty 1 of S1N11A is required for HPE SimpliVity 380 Gen10 Plus 6x SSD
- Qty 1 of S1N12A is required for HPE SimpliVity 380 Gen10 Plus 8x SSD
- Qty 1 of S1N13A- is required for HPE SimpliVity 380 Gen10 Plus 9x SSD

3.84TB SSD 1 Processor based model selection:

- Qty 1 of S1N07A is required for HPE SimpliVity 380 Gen10 Plus 6x SSD
- Qty 1 of S1N08A is required for HPE SimpliVity 380 Gen10 Plus 8x SSD
- Qty 1 of S1N09A- is required for HPE SimpliVity 380 Gen10 Plus 9x SSD
- Qty 1 of S1N10A- is required for HPE SimpliVity 380 Gen10 Plus 12x SSD

3.84TB SSD 2 Processor based model selection:

- Qty 1 of S1N15A is required for HPE SimpliVity 380 Gen10 Plus 6x SSD
- Qty 1 of S1N16A is required for HPE SimpliVity 380 Gen10 Plus 8x SSD
- Qty 1 of S1N17A- is required for HPE SimpliVity 380 Gen10 Plus 9x SSD
- Qty 1 of S1N18A- is required for HPE SimpliVity 380 Gen10 Plus 12x SSD

Remarks	Description	SKU
	HPE SimpliVity 380 G 1 Processor 1.92TB 6 SSD RTU	S1N03A
	HPE SimpliVity 380 G 1 Processor 1.92TB 8 SSD RTU	S1N04A
	HPE SimpliVity 380 G 1 Processor 1.92TB 9 SSD RTU	S1N05A
	HPE SimpliVity 380 G 1 Processor 3.84TB 6 SSD RTU	S1N07A
	HPE SimpliVity 380 G 1 Processor 3.84TB 8 SSD RTU	S1N08A
	HPE SimpliVity 380 G 1 Processor 3.84TB 9 SSD RTU	S1N09A
	HPE SimpliVity 380 G 1 Processor 3.84TB 12 SSD RTU	S1N10A
	HPE SimpliVity 380 G 2 Processors 1.92TB 6 SSD RTU	S1N11A
	HPE SimpliVity 380 G 2 Processors 1.92TB 8 SSD RTU	S1N12A
	HPE SimpliVity 380 G 2 Processors 1.92TB 9 SSD RTU	S1N13A
	HPE SimpliVity 380 G 2 Processors 3.84TB 6 SSD RTU	S1N15A
	HPE SimpliVity 380 G 2 Processors 3.84TB 8 SSD RTU	S1N16A
	HPE SimpliVity 380 G 2 Processors 3.84TB 9 SSD RTU	S1N17A
	HPE SimpliVity 380 G 2 Processors 3.84TB 12 SSD RTU	S1N18A



## Configuration Information

### HPE Integrated Lights Out Advanced Software (iLO Advanced)

**Action:** The HPE iLO Advanced license is required

Remarks	Description	SKU
	HPE iLO Advanced 1-server License with 3yr Support on iLO Licensed Features	BD505A
	HPE iLO Advanced Flexible Quantity License with 3yr Support on iLO Licensed Features	BD506A
	HPE iLO Advanced AKA Tracking License with 3yr Support on iLO Licensed Features	BD507A
	HPE iLO Advanced Electronic License with 3yr Support on iLO Licensed Features	E6U64ABE

### HPE SimpliVity 380 Gen10: Overview for New System

Use the following steps to order a new SimpliVity 380 Gen10 system: processors, memory, storage, networking, power, other optional HW

**Step 1:** Begin with the base node

**Step 2:** Select the hardware options to add to the base node:

**Step 3:** The software license that corresponds to the node configuration will be automatically added

**Step 4:** Select service and support.

#### Step 1: Begin with the base node

##### Base Node

Select the base node

##### Description

HPE SimpliVity 380 Gen10 Node

VMware ESXi Option

**SKU**

Q8D81A

#001

#### Step 2: Select the hardware options to add to the base node

##### 2nd Generation Intel® Xeon® Scalable Processors

###### Action:

- Select CPUs for the node
- In the case of Single CPU only L21 SKU will be included by the configurator.
- In the case of dual CPU: both the L21 and the B21 SKU will be included by the configurator.

##### Primary

Remarks	Description	SKU
8C 2.1GHz 85W	Intel Xeon-Silver 4208 (2.1GHz/8-core/85W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02491-L21
10C 2.2GHz 85W	Intel Xeon-Silver 4210 (2.2GHz/10-core/85W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02492-L21
12C 2.2GHz 85W	Intel Xeon-Silver 4214 (2.2GHz/12-core/85W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02493-L21
16C 2.1GHz 100W	Intel Xeon-Silver 4216 (2.1GHz/16-core/100W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02495-L21
10C 2.5GHz 85W	Intel Xeon-Gold 5215 (2.5GHz/10-core/85W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02496-L21



## Configuration Information

Remarks	Description	SKU
8C 3.0GHz 125W	Intel Xeon-Gold 5217 (3.0GHz/8-core/115W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02497-L21
16C 2.3GHz 125W	Intel Xeon-Gold 5218 (2.3GHz/16-core/125W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02498-L21
18C 2.2GHz 125W	Intel Xeon-Gold 5220 (2.2GHz/18-core/125W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02499-L21
12C 2.7GHz 125W	Intel Xeon-Gold 6226 (2.7GHz/12-core/125W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02501-L21
20C 2.1GHz 125W	Intel Xeon-Gold 6230 (2.1GHz/20-core/125W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02502-L21
8C 3.3GHz 130W	Intel Xeon-Gold 6234 (3.3GHz/8-core/130W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02503-L21
22C 2.1GHz 140W	Intel Xeon-Gold 6238 (2.1GHz/22-core/140W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02504-L21
18C 2.6GHz 150W	Intel Xeon-Gold 6240 (2.6GHz/18-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02509-L21
16C 2.8GHz 150W	Intel Xeon-Gold 6242 (2.8GHz/16-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02510-L21
8C 3.7GHz 150W	Intel Xeon-Gold 6244 (3.6GHz/8-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02512-L21
20C 2.5GHz 150W	Intel Xeon-Gold 6248 (2.5GHz/20-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02514-L21
24C 2.1GHz 150W	Intel Xeon-Gold 6252 (2.1GHz/24-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02516-L21
18C 3.1GHz 200W	Intel Xeon-Gold 6254 (3.1GHz/18-core/200W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02517-L21
24C 2.4GHz 165W	Intel Xeon-Platinum 8260 (2.4GHz/24-core/165W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02521-L21
24C 2.9GHz 205W	Intel Xeon-Platinum 8268 (2.9GHz/24-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02524-L21
28C 2.2GHz 165W	Intel Xeon-Platinum 8276 (2.2GHz/28-core/165W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02526-L21
28C 2.7GHz 205W	Intel Xeon-Platinum 8280 (2.7GHz/28-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02527-L21
12C 3.3GHz 165W	Intel Xeon-Gold 6246 (3.3GHz/12-core/165W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P15758-L21
8C 1.9GHz 85W	Intel Xeon-Bronze 3206R (1.9GHz/8-core/85W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P23547-L21
10C 2.4GHz 100W	Intel Xeon-Silver 4214R (2.4GHz/12-core/100W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P23550-L21
8C 3.2GHz 130W	Intel Xeon-Silver 4215R (3.2GHz/8-core/130W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24465-L21
20C 2.1GHz 125W	Intel Xeon-Gold 5218R (2.1GHz/20-core/125W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24466-L21
24C 2.2GHz 150W	Intel Xeon-Gold 5220R (2.2GHz/24-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P23553-L21
16C 2.9GHz 150W	Intel Xeon-Gold 6226R (2.9GHz/16-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24467-L21
26C 2.1GHz 150W	Intel Xeon-Gold 6230R (2.1GHz/26-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24468-L21



## Configuration Information

Remarks	Description	SKU
28C 2.2GHz 165W	Intel Xeon-Gold 6238R (2.2GHz/28-core/165W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24469-L21
24C 2.4GHz 165W	Intel Xeon-Gold 6240R (2.4GHz/24-core/165W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24470-L21
20C 3.1GHz 205W	Intel Xeon-Gold 6242R (3.1GHz/20-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24471-L21
16C 3.4GHz 205W	Intel Xeon-Gold 6246R (3.4GHz/16-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24472-L21
24C 3.0GHz 205W	Intel Xeon-Gold 6248R (3.0GHz/24-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24473-L21
28C 2.7GHz 205W	Intel Xeon-Gold 6258R (2.7GHz/28-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24474-L21
<b>Secondary</b>		
Remarks	Description	SKU
8C 2.1GHz 85W	Intel Xeon-Silver 4208 (2.1GHz/8-core/85W) Processor Kit for HPE ProLiant DL380 Gen10	P02491-B21
10C 2.2GHz 85W	Intel Xeon-Silver 4210 (2.2GHz/10-core/85W) Processor Kit for HPE ProLiant DL380 Gen10	P02492-B21
12C 2.2GHz 85W	Intel Xeon-Silver 4214 (2.2GHz/12-core/85W) Processor Kit for HPE ProLiant DL380 Gen10	P02493-B21
16C 2.1GHz 100W	Intel Xeon-Silver 4216 (2.1GHz/16-core/100W) Processor Kit for HPE ProLiant DL380 Gen10	P02495-B21
10C 2.5GHz 85W	Intel Xeon-Gold 5215 (2.5GHz/10-core/85W) Processor Kit for HPE ProLiant DL380 Gen10	P02496-B21
8C 3.0GHz 125W	Intel Xeon-Gold 5217 (3.0GHz/8-core/115W) Processor Kit for HPE ProLiant DL380 Gen10	P02497-B21
16C 2.3GHz 125W	Intel Xeon-Gold 5218 (2.3GHz/16-core/125W) Processor Kit for HPE ProLiant DL380 Gen10	P02498-B21
18C 2.2GHz 125W	Intel Xeon-Gold 5220 (2.2GHz/18-core/125W) Processor Kit for HPE ProLiant DL380 Gen10	P02499-B21
12C 2.7GHz 125W	Intel Xeon-Gold 6226 (2.7GHz/12-core/125W) Processor Kit for HPE ProLiant DL380 Gen10	P02501-B21
20C 2.1GHz 125W	Intel Xeon-Gold 6230 (2.1GHz/20-core/125W) Processor Kit for HPE ProLiant DL380 Gen10	P02502-B21
8C 3.3GHz 130W	Intel Xeon-Gold 6234 (3.3GHz/8-core/130W) Processor Kit for HPE ProLiant DL380 Gen10	P02503-B21
22C 2.1GHz 140W	Intel Xeon-Gold 6238 (2.1GHz/22-core/140W) Processor Kit for HPE ProLiant DL380 Gen10	P02504-B21
18C 2.6GHz 150W	Intel Xeon-Gold 6240 (2.6GHz/18-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P02509-B21
16C 2.8GHz 150W	Intel Xeon-Gold 6242 (2.8GHz/16-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P02510-B21
8C 3.7GHz 150W	Intel Xeon-Gold 6244 (3.6GHz/8-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P02512-B21
20C 2.5GHz 150W	Intel Xeon-Gold 6248 (2.5GHz/20-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P02514-B21
24C 2.1GHz 150W	Intel Xeon-Gold 6252 (2.1GHz/24-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P02516-B21
18C 3.1GHz 200W	Intel Xeon-Gold 6254 (3.1GHz/18-core/200W) Processor Kit for HPE ProLiant DL380 Gen10	P02517-B21



## Configuration Information

Remarks	Description	SKU
24C 2.4GHz 165W	Intel Xeon-Platinum 8260 (2.4GHz/24-core/165W) Processor Kit for HPE ProLiant DL380 Gen10	P02521-B21
24C 2.9GHz 205W	Intel Xeon-Platinum 8268 (2.9GHz/24-core/205W) Processor Kit for HPE ProLiant DL380 Gen10	P02524-B21
28C 2.2GHz 165W	Intel Xeon-Platinum 8276 (2.2GHz/28-core/165W) Processor Kit for HPE ProLiant DL380 Gen10	P02526-B21
28C 2.7GHz 205W	Intel Xeon-Platinum 8280 (2.7GHz/28-core/205W) Processor Kit for HPE ProLiant DL380 Gen10	P02527-B21
12C 3.3GHz 165W	Intel Xeon-Gold 6246 (3.3GHz/12-core/165W) Processor Kit for HPE ProLiant DL380 Gen10	P15758-B21
8C 1.9GHz 85W	Intel Xeon-Bronze 3206R (1.9GHz/8-core/85W) Processor Kit for HPE ProLiant DL380 Gen10	P23547-B21
10C 2.4GHz 100W	Intel Xeon-Silver 4210R (2.4GHz/10-core/100W) Processor Kit for HPE ProLiant DL380 Gen10	P23549-B21
12C 2.4GHz 100W	Intel Xeon-Silver 4214R (2.4GHz/12-core/100W) Processor Kit for HPE ProLiant DL380 Gen10	P23550-B21
8C 3.2GHz 130W	Intel Xeon-Silver 4215R (3.2GHz/8-core/130W) Processor Kit for HPE ProLiant DL380 Gen10	P24465-B21
20C 2.1GHz 125W	Intel Xeon-Gold 5218R (2.1GHz/20-core/125W) Processor Kit for HPE ProLiant DL380 Gen10	P24466-B21
24C 2.2GHz 150W	Intel Xeon-Gold 5220R (2.2GHz/24-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P23553-B21
16C 2.9GHz 150W	Intel Xeon-Gold 6226R (2.9GHz/16-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P24467-B21
26C 2.1GHz 150W	Intel Xeon-Gold 6230R (2.1GHz/26-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P24468-B21
28C 2.2GHz 165W	Intel Xeon-Gold 6238R (2.2GHz/28-core/165W) Processor Kit for HPE ProLiant DL380 Gen10	P24469-B21
24C 2.4GHz 165W	Intel Xeon-Gold 6240R (2.4GHz/24-core/165W) Processor Kit for HPE ProLiant DL380 Gen10	P24470-B21
20C 3.1GHz 205W	Intel Xeon-Gold 6242R (3.1GHz/20-core/205W) Processor Kit for HPE ProLiant DL380 Gen10	P24471-B21
16C 3.4GHz 205W	Intel Xeon-Gold 6246R (3.4GHz/16-core/205W) Processor Kit for HPE ProLiant DL380 Gen10	P24472-B21
24C 3.0GHz 205W	Intel Xeon-Gold 6248R (3.0GHz/24-core/205W) Processor Kit for HPE ProLiant DL380 Gen10	P24473-B21
28C 2.7GHz 205W	Intel Xeon-Gold 6258R (2.7GHz/28-core/205W) Processor Kit for HPE ProLiant DL380 Gen10	P24474-B21

### Memory

#### Action:

- Select a memory capacity for the node
- The appropriate memory and quantity will be included by the configurator
- 1 Kit required per CPU

### DDR4-2933

Remarks	Description	SKU
6x 8GB AND 6x 16GB RDIMMs	HPE SimpliVity 144G(6x8/6x16) RDIMM Kit	R4C18A
12x 16GB RDIMMs	HPE SimpliVity 192GB (12x16GB) DDR4-2933 Registered Memory Kit	R4C19A
6x 32GB RDIMMs	HPE SimpliVity 192GB (6x32GB) DDR4-2933 Registered Memory Kit	R4C20A



## Configuration Information

Remarks	Description	SKU
6x 32GB AND 6x 8GB RDIMMs	HPE SimpliVity 240GB (6x32GB/6x8GB) DDR4-2933 Registered Memory Kit	R4C21A
4x 64GB RDIMMs	HPE SimpliVity 256GB (4x64GB) DDR4-2933 Registered Memory Kit	R4C22A
8x 32GB LRDIMMs	HPE SimpliVity 256GB (8x32GB) DDR4-2933 Registered Memory Kit	R4C23A
6x 32GB AND 6x 16GB RDIMMs	HPE SimpliVity 288GB (6x32GB/6x16GB) DDR4-2933 Registered Memory Kit	R4C26A
12x 32GB RDIMMs	HPE SimpliVity 384GB (12x32GB) DDR4-2933 Registered Memory Kit	R4C27A
6x 64GB RDIMMs	HPE SimpliVity 384GB (6x64GB) DDR4-2933 Registered Memory Kit	R4C28A
8x 64GB RDIMMs	HPE SimpliVity 512GB (8x64GB) DDR4-2933 Registered Memory Kit	R4C24A
6x 128GB LRDIMMs	HPE SimpliVity 768GB (6x128GB) DDR4-2933 Load Reduced Memory Kit	R4C30A
12x 64GB RDIMMs	HPE SimpliVity 768GB (12x64GB) DDR4-2933 Registered Memory Kit	R4C29A
12x 128GB LRDIMMs	HPE SimpliVity 1.5TB (12x128GB) DDR4-2933 Load Reduced Memory Kit	R4C25A

**Notes:** For more information go to: <http://www.hpe.com/docs/memory-population-rules>

### Boot Device/Boot RAID Controllers

Description	SKU
HPE Smart Array E208i-p SR Gen10 (8 Internal Lanes/No Cache) 12G SAS PCIe Plug-in Controller	804394-B21
HPE NS204i-p x2 Lanes NVMe PCIe3 x8 OS Boot Device	P12965-B21

**Notes:**

- User must select qty1 of the same type of controller from the above options
- If selecting NS204i-p, there is no need to select boot SSDs below

### Boot SSD Drives

Description	SKU
HPE 300GB SAS 12G Mission Critical 10K SFF SC 3-year Warranty Multi Vendor HDD	872475-K21
HPE 480GB SATA 6G Read Intensive SFF BC PM893 SSD	P44007-K21

**Notes:**

- User must select qty2 of the same type of HDD/SSD
- If selecting NS204i-p Controller, there is no need to select boot SSDs since NS204i-p it comes with NVMe drives

### Networking

**Action:** A 10GbE FlexLOM is required. This is in addition to the standard 4 port 1GbE LOM included in the base node.

Remarks	Description	SKU
	HPE FlexFabric 10Gb 2-port FLR-SFP+ 57810S Adapter	700751-B21
	HPE FlexFabric 10Gb 2-port FLR-T 57810S Adapter	700759-B21
	HPE Ethernet 10/25Gb 2-port FLR-SFP28 MCX4121A-ACFT Adapter	817749-B21
	HPE FlexFabric 10Gb 4-port FLR-T 57840S Adapter	764302-B21

### PCI Adapter

**Action:** Additional PCI Adapters can be added in the case of dual socket with secondary riser.

System Max.	Description	SKU
3	HPE Ethernet 1Gb 4-port BASE-T BCM5719 Adapter	647594-B21
3	HPE Ethernet 10Gb 2-port SFP+ 57810S Adapter	652503-B21
3	HPE Ethernet 1Gb 4-port BASE-T I350-T4V2 Adapter	811546-B21
3	HPE Ethernet 10/25Gb 2-port SFP28 MCX4121A-ACUT Adapter	817753-B21



## Configuration Information

### Power Supplies

**Action:** Two power supplies are required.

Remarks	Description	SKU
	HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit	865414-B21
	HPE 800W Flex Slot Universal Hot Plug Low Halogen Power Supply Kit	865428-B21
	HPE 800W Flex Slot -48VDC Hot Plug Low Halogen Power Supply Kit	865434-B21
	HPE 800W Flex Slot Titanium Hot Plug Low Halogen Power Supply Kit	865438-B21
	HPE 1600W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit	830272-B21
	HPE 1800W-2200W Flex Slot Titanium Hot Plug Low Halogen Power Supply Kit	P44712-B21

### Notes:

- The power supply requirement can vary based on configuration and environment. 800W Power Supply is only supported with specific configurations. Please refer to HPE Power Advisor for proper power sizing.
- All configured nodes ship with a standard 6-foot IEC C-13/C-14 jumper cord (A0K02A). This jumper cord is also included with each standard AC power supply option kit. If a different power cord is required, please check the ProLiant Power Cables web page.

<https://www.hpe.com/us/en/pdfViewer.html?resource=/content/hpe/country/us/en/resources/integrated-systems/reference-guide/power-cords-and-cables>

### Optional Fibre Channel HBA cards

**Action:** Optional FC HBAs may be added if slots are available

System Max.	Description	SKU
3	HPE SN1100Q 16Gb Dual Port Fibre Channel Host Bus Adapter	P9D94A
3	HPE SN1600Q 32Gb Dual Port Fibre Channel Host Bus Adapter	P9M76A

### Optional GPUs

**Action:** Optional Graphic Accelerator (1) may be added in the case of dual CPU with secondary riser.

System Max.	Description	SKU
1	NVIDIA A16 64GB PCIe Non-CEC Accelerator for HPE	R8T26C
1	NVIDIA A40 48GB PCIe Non-CEC Accelerator for HPE	R9S37C

### Power Cord Options

**Action:** Additional hardware options are available

Remarks	Description	SKU
	HPE C13 - GB-1002 CN 250V 10Amp 1.83m Power Cord	AF557A
	HPE C13 - KSC- 8305 KR 250V 10Amp 1.83m Power Cord	AF560A
	HPE C13 - CNS-690 TW 110V 13Amp 1.83m Power Cord	AF561A
	HPE C13 - IS-1293 IN 240V 6Amp LV 2.0m Power Cord	AF562A
	HPE SAFDGRID-SAFDGRID 277V 15Amp DC 2.0m Jumper Cord	J6X00A
	HPE 48VDC 2.85m Power Cable	Q0H80A
	HPE C13 - Nema 5-15P US/CA 110V 10Amp 1.83m Power Cord	AF556A
	HPE C13 - IRAM -2073 AR 250V 10A 2.5m Power Cord	AF558A
	HPE C13 - Nema 5-15P TH/PH 250V 10Amp 1.83m Power Cord	AF559A
	HPE C13 - SEV 1011 CH 250V 10Amp 1.83m Power Cord	AF565A
	HPE C13 - DK-2.5A DK 250V 10Amp 1.83m Power Cord	AF566A
	HPE C13 - CEE-VII EU 250V 10Amp 1.83m Power Cord	AF568A
	HPE C13 - AS3112-3 AU 250V 10Amp 2.5m Power Cord	AF569A
	HPE C13 - SI-32 IL 250V 10Amp 1.83m Power Cord	AF564A
	HPE C13 - JIS C8303 JP 100V 12Amp 2.0m Power Cord	AF572A
	HPE C13 - BS-1363A UK/HK/SG 250V 10Amp 1.83m Power Cord	AF570A

### Notes:

- Network cables and transceivers are available in the HPE Aruba Networking and DataCenter Networking menus.
- Information on interoperability between network adapters, transceivers, and cables is available in network adapter QuickSpecs.





## Configuration Information

- For more information on HPE rack enclosures, review the QuickSpecs at: <https://www.hpe.com/us/en/product-catalog/servers/server-racks.hits-12.html>.

### Additional Server Options

**Action:** Additional hardware options are available

Remarks	Description	SKU
	HPE DL380 Gen10 SFF Systems Insight Display Kit	826703-B21
	HPE DL3XX Gen10 Rear Serial Cable and Enablement Kit	873770-B21
	HPE 2U Small Form Factor Ball Bearing Rail Kit	720863-B21
Remarks	Description	SKU
	HPE 2U Cable Management Arm for Ball Bearing Rail Kit	720865-B21
	HPE 2U Small Form Factor Easy Install Rail Kit	733660-B21

### Storage

Effective capacity varies by environment and is a function of realized deduplication and compression rates. The capacities in this table offer a conservative range based on compression and deduplication rates found in standard, primary storage use cases.

#### Action:

- Select the quantity of SSDs for the node
- The appropriate OmniStack software will be included by the configurator

Models	Description	SKU
<b>Read Intensive</b>		
XS (5x 960Gb)	HPE SimpliVity 960GB SATA 6G Read Intensive SFF SC Multi Vendor SSD	S1J83A
S (5x 1.92TB)	HPE SimpliVity 1.92TB SATA 6G Read Intensive SFF SC Multi Vendor SSD	S1J84A
M (9x 1.92TB)	HPE SimpliVity 1.92TB SATA 6G Read Intensive SFF SC Multi Vendor SSD	S1J84A
L (12x 1.92TB)	HPE SimpliVity 1.92TB SATA 6G Read Intensive SFF SC Multi Vendor SSD	S1J84A
XL (12x 3.84TB)	HPE SimpliVity 3.84TB SATA 6G Read Intensive SFF SC Multi Vendor SSD	S1J85A
<b>Mixed Use</b>		
S (5x 1.92TB)	HPE SimpliVity 1.92TB SATA 6G Mixed Use SFF SC Multi Vendor SSD	S1J92A
M (9x 1.92TB)	HPE SimpliVity 1.92TB SATA 6G Mixed Use SFF SC Multi Vendor SSD	S1J92A
L (12x 1.92TB)	HPE SimpliVity 1.92TB SATA 6G Mixed Use SFF SC Multi Vendor SSD	S1J92A

## Step 3: The software license that corresponds to the node configuration will be automatically added

### Software

#### HPE OmniStack Software

##### Action:

- Based on the hardware configurations selected, the appropriate software will be included by the configurator.
- The software is determined by CPU and storage configuration and is required.

Remarks	Description	SKU
	HPE OmniStack 1P Extra Small SW	Q8A57A
	HPE OmniStack 2P Extra Small SW	Q8A58A
	HPE OmniStack 1P Small SW	Q8A59A
	HPE OmniStack 2P Small SW	Q8A60A
	HPE OmniStack 1P Medium SW	Q8A61A
	HPE OmniStack 2P Medium SW	Q8A62A
	HPE OmniStack 1P Large SW	Q8A63A
	HPE OmniStack 2P Large SW	Q8A64A
	HPE OmniStack 1P Extra Large SW	Q9J86A
	HPE OmniStack 2P Extra Large SW	Q9J87A



## Configuration Information

### HPE Integrated Lights Out Advanced Software (iLO Advanced)

**Action:** The HPE iLO Advanced license is required

Remarks	Description	SKU
	HPE iLO Advanced 1-server License with 3yr Support on iLO Licensed Features	BD505A

### HPE SimpliVity 380 Gen10 G: Overview for New System

Use the following steps to order a new SimpliVity 380 Gen10 system:

**Step 1:** Begin with the base node

**Step 2:** Select the hardware options to add to the base node: processors, memory, storage, networking, power, other optional HW

**Step 3:** The software license that corresponds to the node configuration will be automatically added

**Step 4:** Select service and support.

#### Step 1: Begin with the base node

##### Base Node

###### Action:

- Select the base node
- VMware tracking SKU added automatically
- User selection required for Single Disk Resiliency or Dual Disk Resiliency

Remarks	Description	SKU
	HPE SimpliVity 380 Gen10 G Node	R2G96A
	HPE SimpliVity 380 Gen10 NC G Node	R6A82A
	HPE SimpliVity 380 Gen10 Node with VMware Tracking	R2G97A

#### Step 2: Select the hardware options to add to the base node

##### Processors

##### 2nd Generation Intel® Xeon® Scalable Processors

###### Action:

- Select CPUs for the node
- In the case of Single CPU only L21 SKU will be included by the configurator.
- In the case of dual CPU: both the L21 and the B21 SKU will be included by the configurator

##### Primary

Remarks	Description	SKU
8C 2.1GHz 85W	Intel Xeon-Silver 4208 (2.1GHz/8-core/85W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02491-L21
10C 2.2GHz 85W	Intel Xeon-Silver 4210 (2.2GHz/10-core/85W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02492-L21
12C 2.2GHz 85W	Intel Xeon-Silver 4214 (2.2GHz/12-core/85W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02493-L21
16C 2.1GHz 100W	Intel Xeon-Silver 4216 (2.1GHz/16-core/100W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02495-L21
10C 2.5GHz 85W	Intel Xeon-Gold 5215 (2.5GHz/10-core/85W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02496-L21
8C 3.0GHz 125W	Intel Xeon-Gold 5217 (3.0GHz/8-core/115W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02497-L21
16C 2.3GHz 125W	Intel Xeon-Gold 5218 (2.3GHz/16-core/125W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02498-L21
18C 2.2GHz 125W	Intel Xeon-Gold 5220 (2.2GHz/18-core/125W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02499-L21



## Configuration Information

12C 2.7GHz 125W	Intel Xeon-Gold 6226 (2.7GHz/12-core/125W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02501-L21
20C 2.1GHz 125W	Intel Xeon-Gold 6230 (2.1GHz/20-core/125W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02502-L21
8C 3.3GHz 130W	Intel Xeon-Gold 6234 (3.3GHz/8-core/130W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02503-L21
22C 2.1GHz 140W	Intel Xeon-Gold 6238 (2.1GHz/22-core/140W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02504-L21
18C 2.6GHz 150W	Intel Xeon-Gold 6240 (2.6GHz/18-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02509-L21
16C 2.8GHz 150W	Intel Xeon-Gold 6242 (2.8GHz/16-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02510-L21
<b>Remarks</b>	<b>Description</b>	<b>SKU</b>
8C 3.7GHz 150W	Intel Xeon-Gold 6244 (3.6GHz/8-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02512-L21
20C 2.5GHz 150W	Intel Xeon-Gold 6248 (2.5GHz/20-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02514-L21
24C 2.1GHz 150W	Intel Xeon-Gold 6252 (2.1GHz/24-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02516-L21
18C 3.1GHz 200W	Intel Xeon-Gold 6254 (3.1GHz/18-core/200W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02517-L21
24C 2.4GHz 165W	Intel Xeon-Platinum 8260 (2.4GHz/24-core/165W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02521-L21
24C 2.9GHz 205W	Intel Xeon-Platinum 8268 (2.9GHz/24-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02524-L21
28C 2.2GHz 165W	Intel Xeon-Platinum 8276 (2.2GHz/28-core/165W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02526-L21
28C 2.7GHz 205W	Intel Xeon-Platinum 8280 (2.7GHz/28-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02527-L21
12C 3.3GHz 165W	Intel Xeon-Gold 6246 (3.3GHz/12-core/165W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P15758-L21
8C 1.9GHz 85W	Intel Xeon-Bronze 3206R (1.9GHz/8-core/85W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P23547-L21
10C 2.4GHz 100W	Intel Xeon-Silver 4214R (2.4GHz/12-core/100W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P23550-L21
12C 2.4GHz 100W	Intel Xeon-Silver 4214R (2.4GHz/12-core/100W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P23550-L21
8C 3.2GHz 130W	Intel Xeon-Silver 4215R (3.2GHz/8-core/130W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24465-L21
20C 2.1GHz 125W	Intel Xeon-Gold 5218R (2.1GHz/20-core/125W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24466-L21
24C 2.2GHz 150W	Intel Xeon-Gold 5220R (2.2GHz/24-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P23553-L21
16C 2.9GHz 150W	Intel Xeon-Gold 6226R (2.9GHz/16-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24467-L21
26C 2.1GHz 150W	Intel Xeon-Gold 6230R (2.1GHz/26-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24468-L21
28C 2.2GHz 165W	Intel Xeon-Gold 6238R (2.2GHz/28-core/165W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24469-L21
24C 2.4GHz 165W	Intel Xeon-Gold 6240R (2.4GHz/24-core/165W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24470-L21
20C 3.1GHz 205W	Intel Xeon-Gold 6242R (3.1GHz/20-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24471-L21
16C 3.4GHz 205W	Intel Xeon-Gold 6246R (3.4GHz/16-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24472-L21



## Configuration Information

24C 3.0GHz 205W	Intel Xeon-Gold 6248R (3.0GHz/24-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24473-L21
28C 2.7GHz 205W	Intel Xeon-Gold 6258R (2.7GHz/28-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24474-L21

### Secondary

Remarks	Description	SKU
8C 2.1GHz 85W	Intel Xeon-Silver 4208 (2.1GHz/8-core/85W) Processor Kit for HPE ProLiant DL380 Gen10	P02491-B21
10C 2.2GHz 85W	Intel Xeon-Silver 4210 (2.2GHz/10-core/85W) Processor Kit for HPE ProLiant DL380 Gen10	P02492-B21
12C 2.2GHz 85W	Intel Xeon-Silver 4214 (2.2GHz/12-core/85W) Processor Kit for HPE ProLiant DL380 Gen10	P02493-B21
16C 2.1GHz 100W	Intel Xeon-Silver 4216 (2.1GHz/16-core/100W) Processor Kit for HPE ProLiant DL380 Gen10	P02495-B21
10C 2.5GHz 85W	Intel Xeon-Gold 5215 (2.5GHz/10-core/85W) Processor Kit for HPE ProLiant DL380 Gen10	P02496-B21
8C 3.0GHz 125W	Intel Xeon-Gold 5217 (3.0GHz/8-core/115W) Processor Kit for HPE ProLiant DL380 Gen10	P02497-B21
16C 2.3GHz 125W	Intel Xeon-Gold 5218 (2.3GHz/16-core/125W) Processor Kit for HPE ProLiant DL380 Gen10	P02498-B21
18C 2.2GHz 125W	Intel Xeon-Gold 5220 (2.2GHz/18-core/125W) Processor Kit for HPE ProLiant DL380 Gen10	P02499-B21
12C 2.7GHz 125W	Intel Xeon-Gold 6226 (2.7GHz/12-core/125W) Processor Kit for HPE ProLiant DL380 Gen10	P02501-B21
20C 2.1GHz 125W	Intel Xeon-Gold 6230 (2.1GHz/20-core/125W) Processor Kit for HPE ProLiant DL380 Gen10	P02502-B21
8C 3.3GHz 130W	Intel Xeon-Gold 6234 (3.3GHz/8-core/130W) Processor Kit for HPE ProLiant DL380 Gen10	P02503-B21
22C 2.1GHz 140W	Intel Xeon-Gold 6238 (2.1GHz/22-core/140W) Processor Kit for HPE ProLiant DL380 Gen10	P02504-B21
18C 2.6GHz 150W	Intel Xeon-Gold 6240 (2.6GHz/18-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P02509-B21
16C 2.8GHz 150W	Intel Xeon-Gold 6242 (2.8GHz/16-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P02510-B21
8C 3.7GHz 150W	Intel Xeon-Gold 6244 (3.6GHz/8-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P02512-B21
20C 2.5GHz 150W	Intel Xeon-Gold 6248 (2.5GHz/20-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P02514-B21
24C 2.1GHz 150W	Intel Xeon-Gold 6252 (2.1GHz/24-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P02516-B21
18C 3.1GHz 200W	Intel Xeon-Gold 6254 (3.1GHz/18-core/200W) Processor Kit for HPE ProLiant DL380 Gen10	P02517-B21
24C 2.4GHz 165W	Intel Xeon-Platinum 8260 (2.4GHz/24-core/165W) Processor Kit for HPE ProLiant DL380 Gen10	P02521-B21
24C 2.9GHz 205W	Intel Xeon-Platinum 8268 (2.9GHz/24-core/205W) Processor Kit for HPE ProLiant DL380 Gen10	P02524-B21
28C 2.2GHz 165W	Intel Xeon-Platinum 8276 (2.2GHz/28-core/165W) Processor Kit for HPE ProLiant DL380 Gen10	P02526-B21
28C 2.7GHz 205W	Intel Xeon-Platinum 8280 (2.7GHz/28-core/205W) Processor Kit for HPE ProLiant DL380 Gen10	P02527-B21
12C 3.3GHz 165W	Intel Xeon-Gold 6246 (3.3GHz/12-core/165W) Processor Kit for HPE ProLiant DL380 Gen10	P15758-B21
8C 1.9GHz 85W	Intel Xeon-Bronze 3206R (1.9GHz/8-core/85W) Processor Kit for HPE ProLiant DL380 Gen10	P23547-B21



## Configuration Information

Remarks	Description	SKU
10C 2.4GHz 100W	Intel Xeon-Silver 4210R (2.4GHz/10-core/100W) Processor Kit for HPE ProLiant DL380 Gen10	P23549-B21
12C 2.4GHz 100W	Intel Xeon-Silver 4214R (2.4GHz/12-core/100W) Processor Kit for HPE ProLiant DL380 Gen10	P23550-B21
8C 3.2GHz 130W	Intel Xeon-Silver 4215R (3.2GHz/8-core/130W) Processor Kit for HPE ProLiant DL380 Gen10	P24465-B21
20C 2.1GHz 125W	Intel Xeon-Gold 5218R (2.1GHz/20-core/125W) Processor Kit for HPE ProLiant DL380 Gen10	P24466-B21
24C 2.2GHz 150W	Intel Xeon-Gold 5220R (2.2GHz/24-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P23553-B21
16C 2.9GHz 150W	Intel Xeon-Gold 6226R (2.9GHz/16-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P24467-B21
26C 2.1GHz 150W	Intel Xeon-Gold 6230R (2.1GHz/26-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P24468-B21
28C 2.2GHz 165W	Intel Xeon-Gold 6238R (2.2GHz/28-core/165W) Processor Kit for HPE ProLiant DL380 Gen10	P24469-B21
24C 2.4GHz 165W	Intel Xeon-Gold 6240R (2.4GHz/24-core/165W) Processor Kit for HPE ProLiant DL380 Gen10	P24470-B21
20C 3.1GHz 205W	Intel Xeon-Gold 6242R (3.1GHz/20-core/205W) Processor Kit for HPE ProLiant DL380 Gen10	P24471-B21
16C 3.4GHz 205W	Intel Xeon-Gold 6246R (3.4GHz/16-core/205W) Processor Kit for HPE ProLiant DL380 Gen10	P24472-B21
24C 3.0GHz 205W	Intel Xeon-Gold 6248R (3.0GHz/24-core/205W) Processor Kit for HPE ProLiant DL380 Gen10	P24473-B21
28C 2.7GHz 205W	Intel Xeon-Gold 6258R (2.7GHz/28-core/205W) Processor Kit for HPE ProLiant DL380 Gen10	P24474-B21

**Notes:** Network Choice (NC) server models must be selected for 2nd Generation Intel Xeon® Scalable “Refresh” (R) Processors for the SimpliVity 380 G and 380 H Models

### Memory

#### Action:

- Select a memory capacity for the node
- The appropriate memory and quantity will be included by the configurator
- 1 Kit required per CPU

#### DDR4-2933

Remarks	Description	SKU
8x P00920-K21	HPE SimpliVity 128GB (8x16GB) DDR4-2933 Registered Memory Kit	R4C17A
6x P00918-K21, 6xP00920-K21	HPE SimpliVity 144G(6x8/6x16) RDIMM Kit	R4C18A
12x P00920-K21	HPE SimpliVity 192GB (12x16GB) DDR4-2933 Registered Memory Kit	R4C19A
6x P00924-K21	HPE SimpliVity 192GB (6x32GB) DDR4-2933 Registered Memory Kit	R4C20A
6x P00924-K21, 6x P00918-K21	HPE SimpliVity 240GB (6x32GB/6x8GB) DDR4-2933 Registered Memory Kit	R4C21A
4x P00930-K21	HPE SimpliVity 256GB (4x64GB) DDR4-2933 Registered Memory Kit	R4C22A
8x P00924-K21	HPE SimpliVity 256GB (8x32GB) DDR4-2933 Registered Memory Kit	R4C23A
6x P00924-K21, 6x P00922-K21	HPE SimpliVity 288GB (6x32GB/6x16GB) DDR4-2933 Registered Memory Kit	R4C26A
12x P00924-K21	HPE SimpliVity 384GB (12x32GB) DDR4-2933 Registered Memory Kit	R4C27A
6x P00930-K21	HPE SimpliVity 384GB (6x64GB) DDR4-2933 Registered Memory Kit	R4C28A
8x P00930-K21	HPE SimpliVity 512GB (8x64GB) DDR4-2933 Registered Memory Kit	R4C24A
6x P11040-K21	HPE SimpliVity 768GB (6x128GB) DDR4-2933 Load Reduced Memory Kit	R4C30A
12x P00930-K21	HPE SimpliVity 768GB (12x64GB) DDR4-2933 Registered Memory Kit	R4C29A
12x P11040-K21	HPE SimpliVity 1.5TB (12x128GB) DDR4-2933 Load Reduced Memory Kit	R4C25A

## Configuration Information

### Notes:

- For more information go to: <http://www.hpe.com/docs/memory-population-rules>
- DDR4-2933 Memory Kits are only supported with 2nd Generation Intel Xeon Scalable Series Processors and DDR4-2666 Memory Kits are only supported with 1st Generation Intel Xeon Scalable Series Processors

### Boot Device/Boot RAID Controllers

#### Description

	SKU
HPE Smart Array E208i-p SR Gen10 (8 Internal Lanes/No Cache) 12G SAS PCIe Plug-in Controller	804394-B21
HPE NS204i-p x2 Lanes NVMe PCIe3 x8 OS Boot Device	P12965-B21

### Notes:

- User must select qty1 of the same type of controller from the above options
- If selecting NS204i-p, there is no need to select boot SSDs below

### Boot SSD Drives

#### Description

	SKU
HPE SimpliVity 300GB SAS SFF SC Multi Vendor HDD	S1J81A
HPE SimpliVity 480GB SATA 6G Read Intensive SFF SC Multi Vendor SSD	S1J82A

### Notes:

- User must select qty2 of the same type of HDD/SSD
- If selecting NS204i-p Controller, there is no need to select boot SSDs since NS204i-p it comes with NVMe drives

### Networking

**Action:** One FlexLOM is required. This is in addition to the standard 4 port 1GbE LOM included in the base node

System Max	Description	SKU
1	HPE Ethernet 1Gb 4-port FLR-T BCM5719 Adapter	629135-B22
1	HPE Ethernet 1Gb 4-port FLR-T I350-T4V2 Adapter	665240-B21
System Max	Description	SKU
1	HPE FlexFabric 10Gb 2-port FLR-T 57810S Adapter	700759-B21
1	HPE FlexFabric 10Gb 2-port FLR-SFP+ 57810S Adapter	700751-B21
1	HPE FlexFabric 10Gb 4-port FLR-T 57840S Adapter	764302-B21
1	HPE Ethernet 10/25Gb 2-port FLR-SFP28 BCM57414 Adapter	817709-B21
1	HPE Ethernet 10/25Gb 2-port FLR-SFP28 MCX4121A-ACFT Adapter	817749-B21

### PCIe Adapter

**Action:** Optional PCIe Adapters can be added if slots are available. Additional PCIe slots are available in the case of dual CPU with secondary riser

System Max	Description	SKU
5	HPE Ethernet 1Gb 4-port BASE-T BCM5719 Adapter	647594-B21
5	HPE Ethernet 1Gb 4-port BASE-T I350-T4V2 Adapter	811546-B21
5	HPE Ethernet 10Gb 2-port SFP+ 57810S Adapter	652503-B21
5	HPE Ethernet 10/25Gb 2-port SFP28 QL41401-A2G Adapter	867328-B21
5	HPE Ethernet 10/25Gb 2-port SFP28 MCX4121A-ACUT Adapter	817753-B21

### Power Supplies

**Action:** Two power supplies are required.

Remarks	Description	SKU
	HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit	865414-B21
	HPE 800W Flex Slot Universal Hot Plug Low Halogen Power Supply Kit	865428-B21
	HPE 800W Flex Slot -48VDC Hot Plug Low Halogen Power Supply Kit	865434-B21
	HPE 800W Flex Slot Titanium Hot Plug Low Halogen Power Supply Kit	865438-B21
	HPE 1600W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit	830272-B21
	HPE 1800W-2200W Flex Slot Titanium Hot Plug Low Halogen Power Supply Kit	P44712-B21

### Notes:

- The power supply requirement can vary based on configuration and environment. 800W Power Supply is only supported with specific configurations. Please refer to HPE Power Advisor for proper power sizing.



## Configuration Information

- All configured nodes ship with a standard 6-foot IEC C-13/C-14 jumper cord (A0K02A). This jumper cord is also included with each standard AC power supply option kit. If a different power cord is required, please check the ProLiant Power Cables web page. <https://h20195.www2.hpe.com/v2/getpdf.aspx/4AA6-6836ENW.pdf>

### Optional Fibre Channel HBA cards

**Action:** Optional FC HBAs may be added if slots are available

System Max	Description	SKU
5	HPE SN1100Q 16Gb Dual Port Fibre Channel Host Bus Adapter	P9D94A
5	HPE SN1600Q 32Gb Dual Port Fibre Channel Host Bus Adapter	P9M76A

#### Notes:

- Additional network cables and transceivers are available in the HPE Aruba Networking and DataCenter Networking menus.
- Information on interoperability between network adapters, transceivers, and cables is available in network adapter QuickSpecs.

### Optional GPUs

**Action:** Optional Graphic Accelerator (2) may be added in the case of dual CPU with secondary riser

System Max	Description	SKU
1	NVIDIA A16 64GB PCIe Non-CEC Accelerator for HPE	R8T26C
1	NVIDIA A40 48GB PCIe Non-CEC Accelerator for HPE	R9S37C

### Additional Server Options

**Action:** Additional hardware options are available.

Remarks	Description	SKU
	HPE DL380 Gen10 SFF Systems Insight Display Kit	826703-B21
	HPE DL3XX Gen10 Rear Serial Cable and Enablement Kit	873770-B21
	HPE 2U Small Form Factor Ball Bearing Rail Kit	720863-B21
	HPE 2U Cable Management Arm for Ball Bearing Rail Kit	720865-B21
	HPE 2U Small Form Factor Easy Install Rail Kit	733660-B21

### Storage

#### Action:

- Select one storage kit for the node
- Choose either read intensive or mixed-use drive configuration
- The appropriate OmniStack software will be included by the configurator
- Only the Read Intensive SSD drives are supported with the 24x SSD Kits
- Only the Read Intensive SSD drives are supported with the 9x, 18x and 24x SSD Kits

#### Read Intensive

- Qty 6 of S1J84A (6x1.92TB) is required for HPE SimpliVity 380 G 6x SSD
- Qty 8 of S1J84A (8x1.92TB) is required for HPE SimpliVity 380 G 8x SSD
- Qty 9 of S1J84A (9x1.92TB) is required for HPE SimpliVity 380 G 9x SSD
- Qty 12 of S1J84A (12x1.92TB) is required for HPE SimpliVity 380 G 12x SSD
- Qty 16 of S1J84A (16x1.92TB) is required for HPE SimpliVity 380 G 16x SSD
- Qty 18 of S1J84A (18x1.92TB) is required for HPE SimpliVity 380 G 18x SSD
- Qty 24 of S1J84A (24x1.92TB) is required for HPE SimpliVity 380 G 24x SSD

#### Mixed Use (Not available on the 380 G 9x, 18x or 24x SSD Kits)

- Qty 6 of S1J92A (6x1.92TB) is required for HPE SimpliVity 380 G 6x SSD
- Qty 8 of S1J92A (8x1.92TB) is required for HPE SimpliVity 380 G 8x SSD
- Qty 12 of S1J92A (12x1.92TB) is required for HPE SimpliVity 380 G 12x SSD
- Qty 16 of S1J92A (16x1.92TB) is required for HPE SimpliVity 380 G 16x SSD



## Configuration Information

### Step 3: The software license that corresponds to the node configuration will be automatically added

#### HPE SimpliVity Software

**Action:** Based on the number of CPUs in the node, the appropriate software will be included by the configurator.

- Capacity option selection:
  - For 380 x6 SSD 7.5TB capacity option is selected
  - For 380 x8 SSD and x9 SSD 10TB capacity option is selected
  - For 380 x12 SSD 15TB capacity option is selected
  - For 380 x16 SSD and x18 SSD 21TB capacity option is selected
  - For 380 x24 SSD 30TB capacity option is selected

Remarks	Description	SKU
	HPE SimpliVity 380 G 1 Processor 7.5TB Software	R4D13A
	HPE SimpliVity 380 G 2 Processors 7.5TB Software	R4D14A
	HPE SimpliVity 380 1 Processor 10TB Software	R3V05A
	HPE SimpliVity 380 2 Processors 10TB Software	R3V06A
	HPE SimpliVity 380 G 1 Processor 15TB Software	R4D15A
	HPE SimpliVity 380 G 2 Processors 15TB Software	R4D16A
	HPE SimpliVity 380 G 1 Processor 21TB Software	R4D17A
	HPE SimpliVity 380 G 2 Processors 21TB Software	R4D18A
	HPE SimpliVity 380 G 1 Processor 30TB Software	R4D29A
	HPE SimpliVity 380 G 2 Processors 30TB Software	R4D30A

#### HPE Integrated Lights Out Advanced Software (iLO Advanced)

**Action:** The HPE iLO Advanced license is required

Remarks	Description	SKU
	HPE iLO Advanced 1-server License with 3yr Support on iLO Licensed Features	BD505A
	HPE iLO Advanced Flexible Quantity License with 3yr Support on iLO Licensed Features	BD506A
	HPE iLO Advanced AKA Tracking License with 3yr Support on iLO Licensed Features	BD507A
	HPE iLO Advanced Electronic License with 3yr Support on iLO Licensed Features	E6U64ABE

### HPE SimpliVity 380 Gen10 H: Overview for New System

Use the following steps to order a new SimpliVity 380 Gen10 system:

**Step 1:** Begin with the base node

**Step 2:** Select the hardware options to add to the base node: processors, memory, storage, networking, power, other optional HW

**Step 3:** The software license that corresponds to the node configuration will be automatically added

**Step 4:** Select service and support

#### Step 1: Begin with the base node

##### Base Node

**Action:**

- Select the base node
- VMware tracking SKU added automatically

Remarks	Description	SKU
	HPE SimpliVity 380 Gen10 SFF H Node	R4D36A
	HPE SimpliVity 380 Gen10 SFF NC H Node	R6A81A
	HPE SimpliVity 380 Gen10 Node with VMware Tracking	R2G97A





## Configuration Information

### Step 2: Select the hardware options to add to the base node

#### Processors

##### 1st Generation Intel® Xeon® Scalable Processors

###### Action:

- Select CPUs for the node
- In the case of Single CPU only L21 SKU will be included by the configurator.
- In the case of dual CPU: both the L21 and the B21 SKU will be included by the configurator

##### 2nd Generation Intel® Xeon® Scalable Processors

###### Action:

- Select CPUs for the node
- In the case of Single CPU only L21 SKU will be included by the configurator.
- In the case of dual CPU: both the L21 and the B21 SKU will be included by the configurator

#### Primary

Remarks	Description	SKU
8C 2.1GHz 85W	Intel Xeon-Silver 4208 (2.1GHz/8-core/85W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02491-L21
10C 2.2GHz 85W	Intel Xeon-Silver 4210 (2.2GHz/10-core/85W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02492-L21
12C 2.2GHz 85W	Intel Xeon-Silver 4214 (2.2GHz/12-core/85W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02493-L21
16C 2.1GHz 100W	Intel Xeon-Silver 4216 (2.1GHz/16-core/100W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02495-L21
10C 2.5GHz 85W	Intel Xeon-Gold 5215 (2.5GHz/10-core/85W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02496-L21
8C 3.0GHz 125W	Intel Xeon-Gold 5217 (3.0GHz/8-core/115W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02497-L21
16C 2.3GHz 125W	Intel Xeon-Gold 5218 (2.3GHz/16-core/125W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02498-L21
18C 2.2GHz 125W	Intel Xeon-Gold 5220 (2.2GHz/18-core/125W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02499-L21
12C 2.7GHz 125W	Intel Xeon-Gold 6226 (2.7GHz/12-core/125W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02501-L21
20C 2.1GHz 125W	Intel Xeon-Gold 6230 (2.1GHz/20-core/125W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02502-L21
8C 3.3GHz 130W	Intel Xeon-Gold 6234 (3.3GHz/8-core/130W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02503-L21
22C 2.1GHz 140W	Intel Xeon-Gold 6238 (2.1GHz/22-core/140W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02504-L21
18C 2.6GHz 150W	Intel Xeon-Gold 6240 (2.6GHz/18-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02509-L21
16C 2.8GHz 150W	Intel Xeon-Gold 6242 (2.8GHz/16-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02510-L21
8C 3.7GHz 150W	Intel Xeon-Gold 6244 (3.6GHz/8-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02512-L21
20C 2.5GHz 150W	Intel Xeon-Gold 6248 (2.5GHz/20-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02514-L21
24C 2.1GHz 150W	Intel Xeon-Gold 6252 (2.1GHz/24-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02516-L21
18C 3.1GHz 200W	Intel Xeon-Gold 6254 (3.1GHz/18-core/200W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02517-L21
24C 2.4GHz 165W	Intel Xeon-Platinum 8260 (2.4GHz/24-core/165W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02521-L21
24C 2.9GHz 205W	Intel Xeon-Platinum 8268 (2.9GHz/24-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02524-L21



## Configuration Information

28C 2.2GHz 165W	Intel Xeon-Platinum 8276 (2.2GHz/28-core/165W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02526-L21
28C 2.7GHz 205W	Intel Xeon-Platinum 8280 (2.7GHz/28-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02527-L21
12C 3.3GHz 165W	Intel Xeon-Gold 6246 (3.3GHz/12-core/165W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P15758-L21
8C 1.9GHz 85W	Intel Xeon-Bronze 3206R (1.9GHz/8-core/85W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P23547-L21
10C 2.4GHz 100W	Intel Xeon-Silver 4214R (2.4GHz/12-core/100W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P23550-L21
12C 2.4GHz 100W	Intel Xeon-Silver 4214R (2.4GHz/12-core/100W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P23550-L21
8C 3.2GHz 130W	Intel Xeon-Silver 4215R (3.2GHz/8-core/130W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24465-L21
20C 2.1GHz 125W	Intel Xeon-Gold 5218R (2.1GHz/20-core/125W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24466-L21
24C 2.2GHz 150W	Intel Xeon-Gold 5220R (2.2GHz/24-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P23553-L21
16C 2.9GHz 150W	Intel Xeon-Gold 6226R (2.9GHz/16-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24467-L21
26C 2.1GHz 150W	Intel Xeon-Gold 6230R (2.1GHz/26-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24468-L21
28C 2.2GHz 165W	Intel Xeon-Gold 6238R (2.2GHz/28-core/165W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24469-L21
24C 2.4GHz 165W	Intel Xeon-Gold 6240R (2.4GHz/24-core/165W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24470-L21
20C 3.1GHz 205W	Intel Xeon-Gold 6242R (3.1GHz/20-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24471-L21
16C 3.4GHz 205W	Intel Xeon-Gold 6246R (3.4GHz/16-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24472-L21
24C 3.0GHz 205W	Intel Xeon-Gold 6248R (3.0GHz/24-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24473-L21
28C 2.7GHz 205W	Intel Xeon-Gold 6258R (2.7GHz/28-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24474-L21

### Secondary

Remarks	Description	SKU
8C 2.1GHz 85W	Intel Xeon-Silver 4208 (2.1GHz/8-core/85W) Processor Kit for HPE ProLiant DL380 Gen10	P02491-B21
10C 2.2GHz 85W	Intel Xeon-Silver 4210 (2.2GHz/10-core/85W) Processor Kit for HPE ProLiant DL380 Gen10	P02492-B21
12C 2.2GHz 85W	Intel Xeon-Silver 4214 (2.2GHz/12-core/85W) Processor Kit for HPE ProLiant DL380 Gen10	P02493-B21
16C 2.1GHz 100W	Intel Xeon-Silver 4216 (2.1GHz/16-core/100W) Processor Kit for HPE ProLiant DL380 Gen10	P02495-B21
10C 2.5GHz 85W	Intel Xeon-Gold 5215 (2.5GHz/10-core/85W) Processor Kit for HPE ProLiant DL380 Gen10	P02496-B21
8C 3.0GHz 125W	Intel Xeon-Gold 5217 (3.0GHz/8-core/115W) Processor Kit for HPE ProLiant DL380 Gen10	P02497-B21
16C 2.3GHz 125W	Intel Xeon-Gold 5218 (2.3GHz/16-core/125W) Processor Kit for HPE ProLiant DL380 Gen10	P02498-B21
18C 2.2GHz 125W	Intel Xeon-Gold 5220 (2.2GHz/18-core/125W) Processor Kit for HPE ProLiant DL380 Gen10	P02499-B21
12C 2.7GHz 125W	Intel Xeon-Gold 6226 (2.7GHz/12-core/125W) Processor Kit for HPE ProLiant DL380 Gen10	P02501-B21



## Configuration Information

20C 2.1GHz 125W	Intel Xeon-Gold 6230 (2.1GHz/20-core/125W) Processor Kit for HPE ProLiant DL380 Gen10	P02502-B21
8C 3.3GHz 130W	Intel Xeon-Gold 6234 (3.3GHz/8-core/130W) Processor Kit for HPE ProLiant DL380 Gen10	P02503-B21
22C 2.1GHz 140W	Intel Xeon-Gold 6238 (2.1GHz/22-core/140W) Processor Kit for HPE ProLiant DL380 Gen10	P02504-B21
18C 2.6GHz 150W	Intel Xeon-Gold 6240 (2.6GHz/18-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P02509-B21
16C 2.8GHz 150W	Intel Xeon-Gold 6242 (2.8GHz/16-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P02510-B21
8C 3.7GHz 150W	Intel Xeon-Gold 6244 (3.6GHz/8-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P02512-B21
20C 2.5GHz 150W	Intel Xeon-Gold 6248 (2.5GHz/20-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P02514-B21
24C 2.1GHz 150W	Intel Xeon-Gold 6252 (2.1GHz/24-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P02516-B21
18C 3.1GHz 200W	Intel Xeon-Gold 6254 (3.1GHz/18-core/200W) Processor Kit for HPE ProLiant DL380 Gen10	P02517-B21
24C 2.4GHz 165W	Intel Xeon-Platinum 8260 (2.4GHz/24-core/165W) Processor Kit for HPE ProLiant DL380 Gen10	P02521-B21
24C 2.9GHz 205W	Intel Xeon-Platinum 8268 (2.9GHz/24-core/205W) Processor Kit for HPE ProLiant DL380 Gen10	P02524-B21
28C 2.2GHz 165W	Intel Xeon-Platinum 8276 (2.2GHz/28-core/165W) Processor Kit for HPE ProLiant DL380 Gen10	P02526-B21
28C 2.7GHz 205W	Intel Xeon-Platinum 8280 (2.7GHz/28-core/205W) Processor Kit for HPE ProLiant DL380 Gen10	P02527-B21
12C 3.3GHz 165W	Intel Xeon-Gold 6246 (3.3GHz/12-core/165W) Processor Kit for HPE ProLiant DL380 Gen10	P15758-B21
8C 1.9GHz 85W	Intel Xeon-Bronze 3206R (1.9GHz/8-core/85W) Processor Kit for HPE ProLiant DL380 Gen10	P23547-B21
10C 2.4GHz 100W	Intel Xeon-Silver 4210R (2.4GHz/10-core/100W) Processor Kit for HPE ProLiant DL380 Gen10	P23549-B21
12C 2.4GHz 100W	Intel Xeon-Silver 4214R (2.4GHz/12-core/100W) Processor Kit for HPE ProLiant DL380 Gen10	P23550-B21
<b>Remarks</b>	<b>Description</b>	<b>SKU</b>
8C 3.2GHz 130W	Intel Xeon-Silver 4215R (3.2GHz/8-core/130W) Processor Kit for HPE ProLiant DL380 Gen10	P24465-B21
20C 2.1GHz 125W	Intel Xeon-Gold 5218R (2.1GHz/20-core/125W) Processor Kit for HPE ProLiant DL380 Gen10	P24466-B21
24C 2.2GHz 150W	Intel Xeon-Gold 5220R (2.2GHz/24-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P23553-B21
16C 2.9GHz 150W	Intel Xeon-Gold 6226R (2.9GHz/16-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P24467-B21
26C 2.1GHz 150W	Intel Xeon-Gold 6230R (2.1GHz/26-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P24468-B21
28C 2.2GHz 165W	Intel Xeon-Gold 6238R (2.2GHz/28-core/165W) Processor Kit for HPE ProLiant DL380 Gen10	P24469-B21
24C 2.4GHz 165W	Intel Xeon-Gold 6240R (2.4GHz/24-core/165W) Processor Kit for HPE ProLiant DL380 Gen10	P24470-B21
20C 3.1GHz 205W	Intel Xeon-Gold 6242R (3.1GHz/20-core/205W) Processor Kit for HPE ProLiant DL380 Gen10	P24471-B21
16C 3.4GHz 205W	Intel Xeon-Gold 6246R (3.4GHz/16-core/205W) Processor Kit for HPE ProLiant DL380 Gen10	P24472-B21



## Configuration Information

24C 3.0GHz 205W	Intel Xeon-Gold 6248R (3.0GHz/24-core/205W) Processor Kit for HPE ProLiant DL380 Gen10	P24473-B21
28C 2.7GHz 205W	Intel Xeon-Gold 6258R (2.7GHz/28-core/205W) Processor Kit for HPE ProLiant DL380 Gen10	P24474-B21

**Notes:** Network Choice (NC) server models must be selected for 2nd Generation Intel Xeon® Scalable “Refresh” (R) Processors for the SimpliVity 380 G and 380 H Models

### Memory

#### Action:

- Select a memory capacity for the node
- The appropriate memory and quantity will be included by the configurator
- 1 Kit required per CPU

### DDR4-2933

Details	Description	SKU
8x P00920-K21	HPE SimpliVity 128GB (8x16GB) DDR4-2933 Registered Memory Kit	R4C17A
6x P00918-K21, 6xP00920-K21	HPE SimpliVity 144G(6x8/6x16) RDIMM Kit	R4C18A
12x P00920-K21	HPE SimpliVity 192GB (12x16GB) DDR4-2933 Registered Memory Kit	R4C19A
6x P00924-K21	HPE SimpliVity 192GB (6x32GB) DDR4-2933 Registered Memory Kit	R4C20A
6x P00924-K21, 6x P00918-K21	HPE SimpliVity 240GB (6x32GB/6x8GB) DDR4-2933 Registered Memory Kit	R4C21A
4x P00930-K21	HPE SimpliVity 256GB (4x64GB) DDR4-2933 Registered Memory Kit	R4C22A
8x P00924-K21	HPE SimpliVity 256GB (8x32GB) DDR4-2933 Registered Memory Kit	R4C23A
6x P00924-K21, 6x P00922-K21	HPE SimpliVity 288GB (6x32GB/6x16GB) DDR4-2933 Registered Memory Kit	R4C26A
12x P00924-K21	HPE SimpliVity 384GB (12x32GB) DDR4-2933 Registered Memory Kit	R4C27A
6x P00930-K21	HPE SimpliVity 384GB (6x64GB) DDR4-2933 Registered Memory Kit	R4C28A
8x P00930-K21	HPE SimpliVity 512GB (8x64GB) DDR4-2933 Registered Memory Kit	R4C24A
6x P11040-K21	HPE SimpliVity 768GB (6x128GB) DDR4-2933 Load Reduced Memory Kit	R4C30A
12x P00930-K21	HPE SimpliVity 768GB (12x64GB) DDR4-2933 Registered Memory Kit	R4C29A
12x P11040-K21	HPE SimpliVity 1.5TB (12x128GB) DDR4-2933 Load Reduced Memory Kit	R4C25A

#### Notes:

- For more information go to: <http://www.hpe.com/docs/memory-population-rules>
- DDR4-2933 Memory Kits are only supported with 2nd Generation Intel Xeon Scalable Series Processors and DDR4-2666 Memory Kits are only supported with 1st Generation Intel Xeon Scalable Series Processors

### Networking

**Action:** One FlexLOM is required. This is in addition to the standard 4 port 1GbE LOM included in the base node

System Max	Description	SKU
1	HPE Ethernet 1Gb 4-port FLR-T BCM5719 Adapter	629135-B22
1	HPE Ethernet 1Gb 4-port FLR-T I350-T4V2 Adapter	665240-B21
1	HPE FlexFabric 10Gb 2-port FLR-T 57810S Adapter	700759-B21
1	HPE FlexFabric 10Gb 2-port FLR-SFP+ 57810S Adapter	700751-B21
1	HPE FlexFabric 10Gb 4-port FLR-T 57840S Adapter	764302-B21
1	HPE Ethernet 10/25Gb 2-port FLR-SFP28 BCM57414 Adapter	817709-B21
1	HPE Ethernet 10/25Gb 2-port FLR-SFP28 MCX4121A-ACFT Adapter	817749-B21

### PCI Adapter

**Action:** Optional PCIe Adapters can be added if slots are available. Additional PCIe slots are available in the case of dual CPU with secondary riser.

System Max	Description	SKU
5	HPE Ethernet 1Gb 4-port BASE-T BCM5719 Adapter	647594-B21
5	HPE Ethernet 1Gb 4-port BASE-T I350-T4V2 Adapter	811546-B21
5	HPE Ethernet 10Gb 2-port SFP+ 57810S Adapter	652503-B21
5	HPE Ethernet 10/25Gb 2-port SFP28 QL41401-A2G Adapter	867328-B21
5	HPE Ethernet 10/25Gb 2-port SFP28 MCX4121A-ACUT Adapter	817753-B21



## Configuration Information

5	HPE Ethernet 1Gb 4-port BASE-T BCM5719 Adapter	647594-B21
---	--	------------

### Power Supplies

**Action:** Two power supplies are required.

Remarks	Description	SKU
	HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit	865414-B21
	HPE 800W Flex Slot Universal Hot Plug Low Halogen Power Supply Kit	865428-B21
	HPE 800W Flex Slot -48VDC Hot Plug Low Halogen Power Supply Kit	865434-B21
	HPE 800W Flex Slot Titanium Hot Plug Low Halogen Power Supply Kit	865438-B21
	HPE 1600W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit	830272-B21
	HPE 1800W-2200W Flex Slot Titanium Hot Plug Low Halogen Power Supply Kit	P44712-B21

### Notes:

- The power supply requirement can vary based on configuration and environment. 800W Power Supply is only supported with specific configurations. Please refer to HPE Power Advisor for proper power sizing.

<https://www.hpe.com/info/poweradvisor>

- All configured nodes ship with a standard 6-foot IEC C-13/C-14 jumper cord (A0K02A). This jumper cord is also included with each standard AC power supply option kit. If a different power cord is required, please check the ProLiant Power Cables web page. <https://h20195.www2.hpe.com/v2/getpdf.aspx/4AA6-6836ENW.pdf>

### Optional Fibre Channel HBA cards

**Action:** Optional FC HBAs may be added if slots are available

System Max	Description	SKU
5	HPE SN1100Q 16Gb Dual Port Fibre Channel Host Bus Adapter	P9D94A
5	HPE SN1600Q 32Gb Dual Port Fibre Channel Host Bus Adapter	P9M76A

### Notes:

- Additional network cables and transceivers are available in the HPE Aruba Networking and DataCenter Networking menus.
- Information on interoperability between network adapters, transceivers, and cables is available in the network adapter QuickSpecs

### Additional Server Options

**Action:** Two power supplies are required.

Remarks	Description	SKU
	HPE DL3XX Gen10 Rear Serial Cable and Enablement Kit	873770-B21
	HPE 2U Large Form Factor Ball Bearing Rail Kit	720864-B21
	HPE 2U Cable Management Arm for Ball Bearing Rail Kit	720865-B21
	HPE 2U Large Form Factor Easy Install Rail Kit	733662-B21
	HPE 2U Cable Management Arm for Easy Install Rail Kit	733664-B21

### Storage

HPE SimpliVity 380 H uses a hybrid storage configuration containing one kit of SSDs and one kit of HDDs.

#### Action:

- Select SSD + HDD storage kit for the node
- The appropriate OmniStack software will be included by the configurator

Quantity	Description	SKU
4	HPE SimpliVity 1.92TB SATA 6G Mixed Use SFF SC Multi Vendor SSD	S1J92A
1	HPE SimpliVity 1.2TB SAS 12G SFF (2.5in) 20-pack HDD	R4D37A

**Notes:** Usable capacity is the capacity available after RAID and system overheads have been removed, before deduplication and compression is applied

## Step 3: The software license that corresponds to the node configuration will be automatically added

### HPE OmniStack Software

**Action:** Based on the number of CPUs in the node, the appropriate software will be included by the configurator.

Remarks	Description	SKU
	HPE SimpliVity 380 H 1 Processor 20TB Software	R4D19A
	HPE SimpliVity 380 H 2 Processors 20TB Software	R4D20A



## Configuration Information

### HPE Integrated Lights Out Advanced Software (iLO Advanced)

**Action:** The HPE iLO Advanced license is required.

Remarks	Description	SKU
	HPE iLO Advanced 1-server License with 3yr Support on iLO Licensed Features	BD505A
	HPE iLO Advanced Flexible Quantity License with 3yr Support on iLO Licensed Features	BD506A
	HPE iLO Advanced AKA Tracking License with 3yr Support on iLO Licensed Features	BD507A
	HPE iLO Advanced Electronic License with 3yr Support on iLO Licensed Features	E6U64ABE

### HPE SimpliVity 380 Gen10: Storage Expansion/CPU add-on Overview

Use the following steps to expand Storage or perform a CPU add-on for your existing SimpliVity 380 Gen10 node:

**Step 1:** Start with the Expansion SKU

**Step 2:** Add the SW license that correlates to either a storage expansion or a CPU add-on configuration

**Step 3:** Select the hardware options to add either the storage drive kits or additional CPU and memory

**Step 4:** Select service and support to perform the storage upgrade, migration, install and redeployment

#### Step 1: Start with the Expansion Kit SKU

**Action:** Select the Expansion SKU.

Remarks	Description	SKU
	HPE SimpliVity 380 Gen10 Expansion Kit	R1F85A

#### Step 2: If Storage expansion is needed, add the SW license from below that correlates to the desired expansion configuration

**Action:** Select the appropriate SW license according to the desired storage expansion configuration.

Remarks	Description	SKU
	HPE SimpliVity 380 1 Processor Small to Medium Storage Upgrade E-LTU	R1F86AAE
	HPE SimpliVity 380 2 Processors Small to Medium Storage Upgrade E-LTU	R1F88AAE
	HPE SimpliVity 380 1 Processor Medium to Large Storage Upgrade E-LTU	R1F87AAE
	HPE SimpliVity 380 2 Processors Medium to Large Storage Upgrade E-LTU	R1F89AAE

If a CPU add-on is needed, choose from the SW license below that correlate to the desired configuration for adding a second CPU

**Action:** Select the appropriate SW license if you would like to add a second CPU to an existing 1P SimpliVity 380 node.

Remarks	Description	SKU
	HPE SimpliVity 380 Additional Processor Extra Small Storage Upgrade E-LTU	R1F90AAE
	HPE SimpliVity 380 Additional Processor Small Storage Upgrade E-LTU	R1F91AAE
	HPE SimpliVity 380 Additional Processor Medium Storage Upgrade E-LTU	R1F92AAE
	HPE SimpliVity 380 Additional Processor Large Storage Upgrade E-LTU	R1F93AAE
	HPE SimpliVity 380 Additional Processor Extra Large Storage Upgrade E-LTU	R1F94AAE

#### Step 3: Select the hardware options to add either the storage drive kits or additional CPU and memory

**Action:** Select the appropriate storage upgrade kits based on the desired storage expansion configuration.

Quantity	Description	SKU
4 (S to M)	HPE SimpliVity 1.92TB SATA 6G Read Intensive SFF SC Multi Vendor SSD	S1J84A
3 (M to L)	HPE SimpliVity 1.92TB SATA 6G Read Intensive SFF SC Multi Vendor SSD	S1J84A
4 (S to M)	HPE SimpliVity 1.92TB SATA 6G Mixed Use SFF SC Multi Vendor SSD	S1J92A
3 (M to L)	HPE SimpliVity 1.92TB SATA 6G Mixed Use SFF SC Multi Vendor SSD	S1J92A

**Action:** Select these storage option if upgrading from a Small to a Medium configuration

Remarks	Description	SKU
	HPE Smart Array P816i-a SR Gen10 (16 Internal Lanes/4GB Cache/SmartCache) 12G SAS Modular Controller	804338-B21
	HPE DL38X Gen10 SFF Box1/2 Cage/Backplane Kit	826691-B21

**Action:** Select the Processor Heat Sink

Remarks	Description	SKU
	HPE DL380 Gen10 High Performance Heat Sink Kit	826706-B21



## Configuration Information

**Action:** Select the appropriate CPU for performing the CPU add-on to your existing 1P SimpliVity 380 nodes (from the list at the top of the QuickSpecs)

### Step 4: Select service and support to perform the storage upgrade, migration, install and redeployment

HPE provides a full range of support offers for these products. Tech Care is the minimum level of support, but Complete Care is also available.

Contact your local sales representative or channel partner for more details.

Installation services are required for these products. HA124A1#5ZD needs to be ordered in a quantity matching the sum of the software SKUs from Step 2.

### HPE SimpliVity 380 G: Storage Expansion/CPU add-on Overview

Use the following steps to expand Storage or perform a CPU add-on for your existing SimpliVity 380 G node:

**Step 1:** Start with the Expansion SKU

**Step 2:** Add the SW license that correlates to either a storage expansion or a CPU add-on configuration

**Step 3:** Select the hardware options to add either the storage drive kits or additional CPU and memory

**Step 4:** Select service and support to perform the storage upgrade, migration, install and redeployment

#### Step 1: Start with the Expansion Kit SKU

**Action:** Select the Expansion SKU then select ONLY ONE of the Disk Resiliency SKUs

Remarks	Description	SKU
	HPE SimpliVity 380 Gen10 G Expansion Kit	R6U13A
	HPE SimpliVity Node Tracking with Dual Disk Resiliency	R9Z79A
or	HPE SimpliVity Node Tracking with Single Disk Resiliency	R9Z80A

#### Step 2: If Storage expansion is needed, add the SW license from below that correlates to the desired expansion configuration

**Action:** Select the appropriate SW license according to the desired storage expansion configuration.

Choose from one of the following Redeployment Storage Expansion choices

380G x6 SSD → 380G x8 SSD  
 380G x6 SSD → 380G x9 SSD  
 380G x6 SSD → 380G x12 SSD  
 380G x6 SSD → 380G x16 SSD  
 380G x6 SSD → 380G x18 SSD  
 380G x8 SSD → 380G x24 SSD  
 380G x8 SSD → 380G x9 SSD  
 380G x8 SSD → 380G x12 SSD  
 380G x8 SSD → 380G x16 SSD  
 380G x8 SSD → 380G x18 SSD  
 380G x8 SSD → 380G x24 SSD  
 380G x9 SSD → 380G x12 SSD  
 380G x9 SSD → 380G x18 SSD  
 380G x9 SSD → 380G x24 SSD  
 380G x12 SSD → 380G x16 SSD  
 380G x12 SSD → 380G x18 SSD  
 380G x12 SSD → 380G x24 SSD  
 380G x16 SSD → 380G x18 SSD  
 380G x16 SSD → 380G x24 SSD  
 380G x18 SSD → 380G x24 SSD

#### Description

HPE SimpliVity 380 G 1 Processor 1.92TB 6-pack to 8-pack Upgrade E-RTU  
 HPE SimpliVity 380 G 1 Processor 1.92TB 6-pack to 9-pack Upgrade E-RTU

#### SKU

S1N25AAE  
 S1N26AAE







## Configuration Information

HPE SimpliVity 380 G 1 Processor 1.92TB 12-pack to 18-pack Upgrade E-RTU	S1N41AAE
HPE SimpliVity 380 G 1 Processor 1.92TB 12-pack to 24-pack Upgrade E-RTU	S1N42AAE
HPE SimpliVity 380 G 1 Processor 1.92TB 16-pack to 18-pack Upgrade E-RTU	S1N43AAE

### Notes:

- For x6-x9 reuse x6-x8 Software License SKUs
- For x9-x12 reuse x8-x12 Software License SKUs
- For x12-x18 reuse x12-x16 Software License SKUs
- For x8-x9 no need of new licenses, only 1 extra drive needed
- For x16-x18 no need of new licenses, only 2 extra drives needed
- For x18-x24 reuse x16-x24 Software Licenses and add 6 drives

If a CPU add-on is needed, choose from the SW license below that correlate to the desired configuration for adding a second CPU

**Action:** Select the appropriate SW license if you would like to add a second CPU to an existing 1P SimpliVity 380 G node.

Remarks	Description	SKU
	HPE SimpliVity 380 G Additional Processor 1.92TB 6-pack SSD Upgrade E-LTU	R6V22AAE
	HPE SimpliVity 380 G Additional Processor 1.92TB 8-pack SSD Upgrade E-LTU	R6V23AAE
	HPE SimpliVity 380 G Additional Processor 1.92TB 16-pack SSD Upgrade E-LTU	R6V25AAE
	HPE SimpliVity 380 G Additional Processor 1.92TB 24-pack SSD Upgrade E-LTU	R6V26AAE
	HPE SimpliVity 380 G Additional Processor 1.92TB 24-pack SSD Upgrade E-LTU	R6V26AAE

### Notes:

- For additional processor license for 9-pack, use the 8-pack licenses
- For additional processor license for 18-pack, use the 16-pack licenses

### Step 3: Select the hardware options to add either the storage drive kits or additional CPU and memory

**Action:** Select the appropriate SSD quantities based on the desired storage expansion configuration.

Quantity	Description	SKU
Various	HPE SimpliVity 1.92TB SATA 6G Read Intensive SFF SC Multi Vendor SSD	S1J84A
Various	HPE SimpliVity 1.92TB SATA 6G Mixed Use SFF SC Multi Vendor SSD	S1J92A

**Action:** Select the Processor Heat Sink

Remarks	Description	SKU
	HPE DL380 Gen10 High Performance Heat Sink Kit	826706-B21

**Action:** Select the appropriate CPU for performing the CPU add-on to your existing 1P SimpliVity 380 nodes (from the list at the top of the QuickSpecs)

### Step 4: Select service and support to perform the storage upgrade, migration, install and redeployment

HPE provides a full range of support offers for these products. Tech Care is the minimum level of support, but Complete Care is also available.

Contact your local sales representative or channel partner for more details.

Installation services are required for these products. HA124A1#5ZD needs to be ordered in a quantity matching the sum of the software SKUs from Step 2.



## Technical Specifications

### Physical Dimensions

2U form factor: 3.44 x 26.75 x 17.54 in (8.73 x 67.94 x 44.54 cm)

### End-of-life Management and Recycling

Hewlett-Packard offers end-of-life Hewlett Packard Enterprise product return, trade-in, and recycling programs in many geographic areas. For trade-in information, please go to: <http://www.hp.com/go/green>. To recycle your product, please go to: <http://www.hp.com/go/green> or contact your nearest Hewlett Packard Enterprise sales office. Products returned to Hewlett Packard Enterprise will be recycled, recovered or disposed of in a responsible manner.

The EU WEEE directive (2002/95/EC) requires manufacturers to provide treatment information for each product type for use by treatment facilities. This information (product disassembly instructions) is posted on the Hewlett Packard Enterprise web site at: <http://www.hpe.com/recycle>. These instructions may be used by recyclers and other WEEE treatment facilities as well as Hewlett Packard Enterprise OEM customers who integrate and re-sell Hewlett Packard Enterprise equipment.

---



## Summary of Changes

Date	Version History	Action	Description of Change
19-Jan-2024	Version 31	Changed	Configuration Information section was updated. VMware vSphere and vCenter SKUs were removed.
08-Jan-2024	Version 30	Changed	Overview, Standard Features, Service and Support and Configuration Information sections were updated.
10-Jul-2023	Version 29	Changed	Overview, Standard Features, Service and Support, Configuration Information, and Technical Specifications sections were updated
01-May-2023	Version 28	Changed	Overview, Configuration Information and Technical Specifications sections were updated
23-Jan-2023	Version 27	Changed	Format corrections applied Update QS name
07-Nov-2022	Version 26	Changed	Overview, Standard Features and Configuration Information sections were updated Obsolete SKUs were removed
05-Jul-2022	Version 25	Changed	Overview, Service and Support and Configuration Information sections were updated Obsolete SKU – Q0J62A - removed
06-Dec-2021	Version 24	Changed	Overview, Standard Features and Configuration Information sections were updated Storage Expansion Section - SKUs added in Configuration Information for 380 G Expansion Obsolete SKUs were deleted in Configuration Information
18-Oct-2021	Version 23	Changed	Service and Support Pointnext Tech Care and Complete Care information updated
06-Jul-2021	Version 22	Changed	Configuration Information section was updated. Obsolete SKUs were removed from the QuickSpecs.
01-Mar-2021	Version 21	Changed	Overview, Standard Features, Service and Support, and Configuration Information sections were updated.
08-Sep-2020	Version 20	Changed	Configuration Information section was updated.
03-Aug-2020	Version 19	Changed	Overview and Configuration Information sections were updated. New branding applied to document.
04-May-2020	Version 18	Changed	Overview, Standard Features, and Configuration Information sections were updated.
02-Mar-2020	Version 17	Changed	Overview and Configuration Information sections were updated.
03-Feb-2020	Version 16	Changed	Overview, Standard Features and Configuration Information sections were updated.
04-Nov-2019	Version 15	Changed	Overview, Standard Features, and Configuration Information sections were updated. Added HPE SimpliVity 380 Gen10 G Model with 8x SSD drivers, added new 10TB SW Licenses and features for OmniStack Software v3.7.10
24-Oct-2019	Version 14	Added	Updated HPE SimpliVity 380 Gen10 sections
01-Jul-2019	Version 13	Changed	Overview and Configuration Information sections were updated
03-Jun-2019	Version 12	Changed	Added HPE SimpliVity 380 Gen10 G Model., Standard Features section was updated., obsolete SKUs were removed from the QuickSpecs. Service and Support section was updated.





## Summary of Changes

Date	Version History	Action	Description of Change
18-Mar-2019	Version 11	Changed	Configuration Information section was updated.
		Added	SKUs added in Configuration Information: Q8A57A, Q8A58A, Q8A59A, Q8A60A, Q8A61A, Q8A62A, Q8A63A, Q8A64A, Q9J86A, Q9J87A.
		Removed	SKUs deleted in Configuration Information: Q8A57A, Q8A58A, Q8A59A, Q8A60A, Q8A61A, Q8A62A, Q8A63A, Q8A64A, Q9J86A, Q9J87A, Q8A65A, Q8A66A, Q8A67A, Q8A68A, Q8A69A, Q8A70A, Q8A71A, Q8A72A, Q9J88A, Q9J89A.
04-Mar-2019	Version 10	Changed	Overview, Standard Features, and Configuration sections were updated.
		Added	SKUs added in Configuration Information section (additional processors): 871619-L21, 869089-L21, 879423-L21, 871617-L21, 871618-L21, P00756-L21, 879424-L21, 869086-L21, 869088-L21, 871619-B21, 869089-B21, 879423-B21, 871617-B21, 871618-B21, P00756-B21, 879424-B21, 874752-B21, 873645-B21
04-Feb-2019	Version 9	Changed	Overview and Configuration Information sections were updated.
		Added	SKUs added in Configuration Information section: R1F85AAE, R1F86AAE, R1F88AAE, R1F87AAE, R1F89AAE, R1F90AAE, R1F91AAE, R1F92AAE, R1F93AAE, R1F94AAE, R1F81AAE, R1F82AAE, R1F83AAE, R1F84AAE, 804338-B21, 826691-B21, 826846-B21, 826848-B21, 826850-B21, 826852-B21, 826854-B21, 826856-B21, 826862-B21, 826866-B21, 826870-B21, 826878-B21, 826884-B21, 826888-B21, 876562-B21, 826886-B21, 826872-B21, 826860-B21, 826868-B21, 826874-B21, 869090-B21, 826890-B21, 826876-B21, 826882-B21, 826706-B21, R1Q89A, R1Q90A, R1Q91A, R1Q92A, R1Q93A, R1Q94A, R1Q95A, R1Q96A.
07-Jan-2019	Version 8	Changed	Configuration Information section was updated.
		Removed	SKUs were deleted: 871619-L21, 869089-L21, 879423-L21, 874762-L21, 871617-L21, 871618-L21.
05-Nov-2018	Version 7	Changed	Overview, and Configuration Information sections were updated.
		Added	SKUs added in Configuration Information: 764302-B21, Q0V80A.
		Removed	Obsolete SKUs were deleted in Configuration Information: J2R02A, J2R04A
07-May-2018	Version 6	Added	Standard Features and Configuration Information sections were updated.
05-Mar-2018	Version 5	Changed	Overview, Standard Features and Configuration Information sections were updated.
		Added	SKUs were added in Configuration Information section: 826872-B21, 826872-L21, 874762-B21, 874762-L21, Q9J90A, 700759-B21, 817749-B21, Q8A61A, Q8A62A, Q8A63A, Q8A64A, Q9J86A, Q9J87A, Q8A69A, Q8A70A, Q8A71A, Q8A72A, Q9J88A, Q9J89A.
04-Dec-2017	Version 4	Changed	Standard Features, Configuration Information, Service and Support, and Technical Specifications sections were updated.
		Added	SKUs were added in Configuration Information: 874762-L21, Q8D94A, Q5V86A, Q5V87A, Q5V88A, 811546-B21.
06-Nov-2017	Version 3	Changed	Changes made to the document
02-Oct-2017	Version 2	Changed	Changes made to the entire document
25-Sep-2017	Version 1	New	QuickSpecs created.



## Copyright

Make the right purchase decision.  
Contact our presales specialists.



---

© Copyright 2024 Hewlett Packard Enterprise Development LP. The information contained herein is subject to change without notice. The only warranties for Hewlett Packard Enterprise products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. Hewlett Packard Enterprise shall not be liable for technical or editorial errors or omissions contained herein.

Microsoft and Windows NT are US registered trademarks of Microsoft Corporation. Intel is a US registered trademark of Intel Corporation. Unix is a registered trademark of The Open Group.

a00021989enw - 16060 - Worldwide - V31 - 19-January-2024